

# seL4 Reference Manual

## For v3 development branch

### API version 1.2(r2)

---

Trustworthy Systems Team, NICTA  
[ertos@nicta.com.au](mailto:ertos@nicta.com.au)

18 July 2011

© 2011 Open Kernel Labs, Inc.

ALL RIGHTS RESERVED. This document is made available under the terms of the Open Kernel Labs, Inc. NON-COMMERCIAL LICENSE AGREEMENT. A copy of the license is available in the top-level directory of this distribution.

### **Acknowledgements**

This primary authors of this document are Matthew Grosvenor and Adam Walker, with contributions from Adrian Danis, Andrew Boyton, David Greenaway, Etienne Le Sueur, Gernot Heiser, Gerwin Klein, Godfrey van der Linden, Kevin Elphinstone, Matthew Fernandez, Matthias Daum, Michael von Tessin, Peter Chubb, Simon Winwood, Thomas Sewell and Toby Murray. All authors and contributors can be contacted at `firstname.lastname@nicta.com.au`.



# Contents

<b>1</b>	<b>Introduction</b>	<b>1</b>
<b>2</b>	<b>Kernel Services and Objects</b>	<b>2</b>
2.1	Capability-based Access Control . . . . .	2
2.2	System Calls . . . . .	3
2.3	Kernel Objects . . . . .	4
2.4	Kernel Memory Allocation . . . . .	5
2.4.1	Reusing Memory . . . . .	6
<b>3</b>	<b>Capability Spaces</b>	<b>7</b>
3.1	Capability and CSpace Management . . . . .	8
3.1.1	CSpace Creation . . . . .	8
3.1.2	CNode Methods . . . . .	8
3.1.3	Capability Rights . . . . .	9
3.1.4	Capability Derivation Tree . . . . .	9
3.2	Deletion, Revocation, and Recycling . . . . .	10
3.3	CSpace Addressing . . . . .	11
3.3.1	Capability Address Lookup . . . . .	11
3.3.2	Addressing Capabilities . . . . .	12
3.4	Lookup Failure Description . . . . .	14
3.4.1	Invalid Root . . . . .	14
3.4.2	Missing Capability . . . . .	14
3.4.3	Depth Mismatch . . . . .	15
3.4.4	Guard Mismatch . . . . .	15
<b>4</b>	<b>Inter-process Communication</b>	<b>16</b>
4.1	Message Registers . . . . .	16
4.2	Synchronous Endpoints . . . . .	18
4.2.1	Endpoint Badges . . . . .	18
4.2.2	Capability Transfer . . . . .	18
4.2.3	Errors . . . . .	19
4.3	Asynchronous Endpoints . . . . .	19
4.3.1	Asynchronous Endpoint Badges . . . . .	20

4.3.2	Binding Asynchronous Endpoints . . . . .	20
<b>5</b>	<b>Threads and Execution</b>	<b>21</b>
5.1	Threads . . . . .	21
5.1.1	Thread Creation . . . . .	21
5.1.2	Thread Deactivation . . . . .	21
5.1.3	Scheduling . . . . .	21
5.1.4	Exceptions . . . . .	22
5.1.5	Message Layout of the Read-/Write-Registers Methods . . . . .	22
5.2	Faults . . . . .	23
5.2.1	Capability Faults . . . . .	23
5.2.2	Unknown Syscall . . . . .	23
5.2.3	User Exception . . . . .	24
5.2.4	VM Fault . . . . .	25
<b>6</b>	<b>Address Spaces and Virtual Memory</b>	<b>26</b>
6.1	Overview . . . . .	26
6.2	Objects . . . . .	27
6.3	Mapping Attributes . . . . .	28
6.4	Sharing Memory . . . . .	28
6.5	Page Faults . . . . .	29
<b>7</b>	<b>Hardware I/O</b>	<b>30</b>
7.1	Interrupt Delivery . . . . .	30
7.2	IA-32-Specific I/O . . . . .	31
7.2.1	I/O Ports . . . . .	31
7.2.2	I/O Space . . . . .	31
<b>8</b>	<b>System Bootstrapping</b>	<b>33</b>
8.1	Initial Thread's Environment . . . . .	33
8.2	BootInfo Frame . . . . .	34
8.3	Boot Command-line Arguments . . . . .	35
8.4	Multikernel Bootstrapping . . . . .	36
<b>9</b>	<b>seL4 API Reference</b>	<b>38</b>
9.1	Error Codes . . . . .	38
9.1.1	Invalid Argument . . . . .	38
9.1.2	Invalid Capability . . . . .	38
9.1.3	Illegal Operation . . . . .	38
9.1.4	Range Error . . . . .	39
9.1.5	Alignment Error . . . . .	39
9.1.6	Failed Lookup . . . . .	39
9.1.7	Delete First . . . . .	39

---

9.1.8	Revoke First	39
9.2	System Calls	40
9.2.1	Send	40
9.2.2	Wait	40
9.2.3	Call	40
9.2.4	Reply	41
9.2.5	Non-blocking Send	41
9.2.6	Reply Wait	41
9.2.7	Poll	42
9.2.8	Yield	42
9.2.9	Notify	42
9.3	Architecture-Independent Object Methods	43
9.3.1	CNode - Copy	43
9.3.2	CNode - Delete	44
9.3.3	CNode - Mint	45
9.3.4	CNode - Move	46
9.3.5	CNode - Mutate	47
9.3.6	CNode - Recycle	48
9.3.7	CNode - Revoke	48
9.3.8	CNode - Rotate	49
9.3.9	CNode - Save Caller	50
9.3.10	Debug - Halt	50
9.3.11	Debug - Put Character	50
9.3.12	IRQ Control - Get	51
9.3.13	IRQ Handler - Acknowledge	51
9.3.14	IRQ Handler - Clear	52
9.3.15	IRQ Handler - Set Endpoint	52
9.3.16	TCB - Bind Asynchronous Endpoint	52
9.3.17	TCB - Unbind Asynchronous Endpoint	53
9.3.18	TCB - Configure	53
9.3.19	TCB - Copy Registers	54
9.3.20	TCB - Read Registers	54
9.3.21	TCB - Resume	55
9.3.22	TCB - Set IPC Buffer	55
9.3.23	TCB - Set Priority	55
9.3.24	TCB - Set Space	56
9.3.25	TCB - Suspend	56
9.3.26	TCB - Write Registers	57
9.3.27	Untyped - Retype	58
9.3.28	Summary of Object Sizes	59
9.4	IA-32-Specific Object Methods	61

---

9.4.1	IA32 ASID Control - Make Pool . . . . .	61
9.4.2	IA32 ASID Pool - Assign . . . . .	61
9.4.3	IA32 IO Port - In 8 . . . . .	62
9.4.4	IA32 IO Port - In 16 . . . . .	62
9.4.5	IA32 IO Port - In 32 . . . . .	62
9.4.6	IA32 IO Port - Out 8 . . . . .	63
9.4.7	IA32 IO Port - Out 16 . . . . .	63
9.4.8	IA32 IO Port - Out 32 . . . . .	63
9.4.9	IA32 IO Page Table - Map . . . . .	64
9.4.10	IA32 Page - Map IO . . . . .	64
9.4.11	IA32 Page - Map . . . . .	65
9.4.12	IA32 Page - Remap . . . . .	65
9.4.13	IA32 Page - Unmap . . . . .	66
9.4.14	IA32 Page Table - Map . . . . .	66
9.4.15	IA32 Page Table - Unmap . . . . .	66
9.5	ARM-Specific Object Methods . . . . .	67
9.5.1	ARM ASID Control - Make Pool . . . . .	67
9.5.2	ARM ASID Pool - Assign . . . . .	67
9.5.3	ARM Page - Flush Caches . . . . .	68
9.5.4	ARM Page - Map . . . . .	68
9.5.5	ARM Page - Remap . . . . .	69
9.5.6	ARM Page - Unmap . . . . .	69
9.5.7	ARM Page Table - Map . . . . .	70
9.5.8	ARM Page Table - Unmap . . . . .	70



# List of Tables

3.1	seL4 access rights. . . . .	9
3.2	Capability Derivation . . . . .	10
4.1	Physical register allocation for IPC messages on the x86 architecture. . . . .	16
4.2	Physical register allocation for IPC messages on the ARM architecture. . . . .	17
4.3	Fields of the <code>seL4_IPCBuffer</code> structure. Note that <code>badges</code> and <code>caps</code> use the same area of memory in the structure. . . . .	17
5.1	Contents of an IPC message. . . . .	23
5.2	Unknown system call outcome on the ARM architecture. . . . .	24
5.3	Unknown system call outcome on the IA-32 architecture. . . . .	24
5.4	User exception outcome on the ARM architecture. . . . .	25
5.5	User exception outcome on the IA-32 architecture. . . . .	25
6.1	Virtual memory attributes for ARM page table entries. . . . .	28
6.2	Virtual memory attributes for IA32 page table entries. . . . .	28
8.1	Initial Thread's CNode Content . . . . .	33
8.2	BootInfo Struct . . . . .	34
8.3	DeviceRegion Struct . . . . .	35
8.4	IA-32 boot command-line arguments . . . . .	36
9.1	Platform Independent Object Sizes . . . . .	59
9.2	IA-32 Specific Object Sizes . . . . .	59
9.3	ARM Specific Object Sizes . . . . .	60

# List of Figures

3.1	Example capability derivation tree. . . . .	10
3.2	An example CSpace demonstrating object references at all levels, various guard and radix sizes and internal CNode references. . . . .	12
3.3	An arbitrary CSpace layout . . . . .	13

# Chapter 1

## Introduction

The seL4 microkernel is an operating-system kernel designed to be a secure, safe, and reliable foundation for systems in a wide variety of application domains. As a microkernel, it provides a small number of services to applications, such as abstractions to create and manage virtual address spaces, threads, and inter-process communication (IPC). The small number of services provided by seL4 directly translates to a small implementation of approximately 8700 lines of C code. This has allowed the ARMv6 version of the kernel to be formally proven in the Isabelle/HOL theorem prover to adhere to its formal specification [Boy09, CKS08, DEK<sup>+</sup>06, EKE08, KEH<sup>+</sup>09, TKN07, WKS<sup>+</sup>09].

This manual describes the seL4 kernel's API from a user's point of view. The document starts by giving a brief overview of the seL4 microkernel design, followed by a reference of the high-level API exposed by the seL4 kernel to userspace.

While we have tried to ensure that this manual accurately reflects the behaviour of the seL4 kernel, this document is by no means a formal specification of the kernel. When the precise behaviour of the kernel under a particular circumstance needs to be known, users should refer to the seL4 abstract specification, which gives a formal description of the seL4 kernel.

Note: This iteration of the manual documents a version of the seL4 kernel that is not currently formally verified. This document serves as a description of the user visible behaviour of features and modifications that may one day be incorporated into the verified seL4 kernel.

## Chapter 2

# Kernel Services and Objects

A limited number of service primitives are provided by the microkernel; more complex services may be implemented as applications on top of these primitives. In this way, the functionality of the system can be extended without increasing the code and complexity in privileged mode, while still supporting a potentially wide number of services for varied application domains.

The basic services seL4 provides are as follows:

**Threads** are an abstraction of CPU execution that supports running software;

**Address spaces** are virtual memory spaces that each contain an application. Applications are limited to accessing memory in their address space;

**Inter-process communication** (IPC) via *endpoints* allows threads to communicate using message passing;

**Device primitives** allow device drivers to be implemented as unprivileged applications. The kernel exports hardware device interrupts via IPC messages; and

**Capability spaces** store capabilities (i.e., access rights) to kernel services along with their book-keeping information.

This chapter gives an overview of these services, describes how kernel objects are accessed by userspace applications, and describes how new objects can be created.

### 2.1 Capability-based Access Control

The seL4 microkernel provides a capability-based access-control model. Access control governs all kernel services; in order to perform an operation, an application must *invoke* a capability in its possession that has sufficient access rights for the requested service. With this, the system can be configured to isolate software components from each other, and also to enable authorised, controlled communication between components by selectively granting specific communication capabilities. This enables software-component isolation with a high degree of assurance, as only those operations explicitly authorised by capability possession are permitted.

A capability is an unforgeable token that references a specific kernel object (such as a thread control block) and carries access rights that control what methods may be

invoked. Conceptually, a capability resides in an application's *capability space*; an address in this space refers to a *slot* which may or may not contain a capability. An application may refer to a capability—to request a kernel service, for example—using the address of the slot holding that capability. This means, the seL4 capability model is an instance of a *segregated* (or *partitioned*) capability model, where capabilities are managed by the kernel.

Capability spaces are implemented as a directed graph of kernel-managed *capability nodes* (CNodes). A CNode is a table of slots, where each slot may contain further CNode capabilities. An address in a capability space is then the concatenation of the indices of the CNode capabilities forming the path to the destination slot; we discuss CNode objects in detail in Chapter 3.

Capabilities can be copied and moved within capability spaces, and also sent via IPC. This allows creation of applications with specific access rights, the delegation of authority to another application, and passing to an application authority to a newly created (or selected) kernel service. Furthermore, capabilities can be *minted* to create a derived capability with a subset of the rights of the original capability (never with more rights). A newly minted capability can be used for partial delegation of authority. Capabilities can also be revoked to withdraw authority. Revocation recursively removes any capabilities that have been derived from the original capability being revoked. The propagation of capabilities through the system is controlled by a *take-grant*-based model [EKE08, Boy09].

## 2.2 System Calls

The seL4 kernel provides a message-passing service for communication between threads. This mechanism is also used for communication with kernel-provided services. There is a standard message format, each message containing a number of data words and possibly some capabilities. The structure and encoding of these messages are described in detail in Chapter 4.

Threads send messages by invoking capabilities within their capability space. When an endpoint capability is invoked in this way the message will be transferred through the kernel to another thread. When capabilities to kernel objects are invoked, the message will be interpreted as a method invocation in a manner specific to the type of kernel object. For example, invoking a thread control block (TCB) capability with a correctly formatted message will suspend the target thread.

The kernel provides the following system calls:

`seL4_Send()` delivers a message through the named capability and then allows the application to continue. If the invoked capability is an endpoint and no receiver is ready to receive the message immediately, the sending thread will be blocked until the message can be delivered. No error code or response will be returned by the receiving thread or kernel object.

`seL4_NBSend()` performs a non-blocking send. It is similar to `seL4_Send()` except that if the message cannot be received immediately, the message is silently dropped. Like `seL4_Send()`, no error code or response will be returned by the object.

`seL4_Call()` is a `seL4_Send()` that blocks the sending thread until a reply message is

received. When the sent message is delivered to another thread (via an `Endpoint`), an additional ‘*reply*’ capability is added to the message and delivered to the receiver to give it the right to reply to the sender. The reply capability is stored in a special purpose slot in the receiver’s TCB. When invoking capabilities to kernel services, using `seL4_Call()` allows the kernel to return an error code or other response within a reply message.

`seL4_Wait()` is used by a thread to receive messages through endpoints. If no message is ready to be sent, the thread will block until a message is sent. This system call works only on endpoint capabilities, raising a fault (see section 5.2) when attempted with other capability types.

`seL4_Reply()` is used to respond to a `seL4_Call()`, using the capability generated by the `seL4_Call()` system call and stored in the replying thread’s TCB. It delivers the message to the calling thread, waking it in the process.

There is space for only one reply capability in each thread’s TCB, so the `seL4_Reply()` syscall can be used to reply to the most recent caller only. The `seL4_CNode_SaveCaller()` method that will be described later can be used to save the reply capability into regular capability space, where it can be used with `seL4_Send()`.

`seL4_ReplyWait()` is a combination of `seL4_Reply()` and `seL4_Wait()`. It exists for efficiency reasons: the common case of replying to a request and waiting for the next can be performed in a single kernel system call instead of two.

`seL4_Poll()` is used by a thread to check for messages waiting to be sent through an endpoint without blocking on that endpoint. This system call works only on asynchronous endpoint capabilities, raising a fault (see section 5.2) when attempted with other capability types.

`seL4_Yield()` is the only system call that does not require a capability to be used. It causes the calling thread to give up the remainder of its timeslice to another runnable thread of the same priority level. If there are no runnable threads with the same priority, the calling thread is resumed and the system call has no effect.

## 2.3 Kernel Objects

In this section we give a brief overview of the kernel-implemented object types whose instances (also simply called *objects*) can be invoked by applications. The interface to these objects forms the interface to the kernel itself. The creation and use of the high-level kernel services is achieved by the creation, manipulation, and combination of these kernel objects:

**CNodes** (see Chapter 3) store capabilities, giving threads permission to invoke methods on particular objects. Each CNode has a fixed number of slots, always a power of two, determined when the CNode is created. Slots can be empty or contain a capability.

**Thread Control Blocks** (TCBs; see Chapter 5) represent a thread of execution in seL4. Threads are the unit of execution that is scheduled, blocked, unblocked, etc., depending on the application's interaction with other threads.

**IPC Endpoints** (see Chapter 4) may be used to facilitate interprocess communication between threads. The seL4 microkernel supports two types of endpoints:

- *Synchronous* endpoints (Endpoint), which cause the sending thread to block until its message is received; and
- *Asynchronous* endpoints (AsyncEP), which only allow short messages to be sent, but do not cause the sender to block.

A capability to an endpoint can be restricted to be send-only or receive-only. Additionally, capabilities to Endpoint objects may be configured to allow capabilities to be transferred across to other threads.

**Virtual Address Space Objects** (see Chapter 6) are used to construct a virtual address space (or VSpace) for one or more threads. These objects largely directly correspond to those of the hardware; that is, a page directory pointing to page tables, which in turn map physical frames. The kernel also includes ASID Pool and ASID Control objects for tracking the status of address spaces.

**Interrupt Objects** (see Chapter 7) give applications the ability to receive and acknowledge interrupts from hardware devices. Initially, there is a capability to IRQControl, which allows for the creation of IRQHandler capabilities. An IRQHandler capability permits the management of a specific interrupt source associated with a specific device. It is delegated to a device driver to access an interrupt source. The IRQHandler object allows threads to wait for and acknowledge individual interrupts.

**Untyped Memory** (see Section 2.4) is the foundation of memory allocation in the seL4 kernel. Untyped memory capabilities have a single method which allows the creation of new kernel objects. If the method succeeds, the calling thread gains access to capabilities to the newly-created object. Additionally, untyped memory objects can be divided into a group of smaller untyped memory objects allowing delegation of part (or all) of the system's memory. We discuss memory management in general in the following sections.

## 2.4 Kernel Memory Allocation

The seL4 microkernel does not dynamically allocate memory for kernel objects. Kernel objects must be explicitly created from application-controlled memory regions via Untyped Memory capabilities. Applications must have explicit authority to memory (via Untyped Memory capabilities) in order to create new objects, and all objects consume constant memory once created. These mechanisms can be used to precisely control the specific amount of physical memory available to applications, including being able to enforce isolation of physical memory access between applications or a device. There are

no arbitrary resource limits in the kernel apart from those dictated by the hardware<sup>1</sup>, and so many denial-of-service attacks via resource exhaustion are avoided.

At boot time, seL4 pre-allocates the memory required for the kernel itself, including the code, data, and stack sections (seL4 is a single kernel-stack operating system). The remainder of the memory is given to the initial thread in the form of capabilities to Untyped Memory, and some additional capabilities to kernel objects that were required to bootstrap the initial thread. These objects can then be split into smaller untyped memory regions or other kernel objects using the `seL4_Untyped_Retype()` method; the created objects are termed *children* of the original untyped memory object.

The user-level application that creates an object using `seL4_Untyped_Retype()` receives full authority over the resulting object. It can then delegate all or part of the authority it possesses over this object to one or more of its clients.

### 2.4.1 Reusing Memory

The model described thus far is sufficient for applications to allocate kernel objects, distribute authority among client applications, and obtain various kernel services provided by these objects. This alone is sufficient for a simple static system configuration.

The seL4 kernel also allows memory reuse. Reusing a region of memory is sound only when there are no dangling references (i.e. capabilities) left to the objects implemented by that memory. The kernel tracks *capability derivations*, that is, the children generated by the various methods (`seL4_Untyped_Retype()`, `seL4_CNode_Mint()`, `seL4_CNode_Copy()`, and `seL4_CNode_Mutate()`). Whenever a user requests that the kernel create new objects in an untyped memory region, the kernel uses this information to check that there are no children in the region, and thus no live capability references.

The tree structure so generated is termed the *capability derivation tree* (CDT).<sup>2</sup> For example, when a user creates new kernel objects by retyping untyped memory, the newly created capabilities would be inserted into the CDT as children of the untyped memory capability.

Finally, the `seL4_CNode_Revoke()` method provided by CNode objects destroys all capabilities derived from the argument capability. Revoking the last capability to a kernel object triggers the *destroy* operation on the now unreferenced object. This simply cleans up any in-kernel dependencies between it, other objects and the kernel. By calling `seL4_CNode_Revoke()` on the original capability to an untyped memory object, the user removes all of the untyped memory object's children—that is, all capabilities pointing to objects in the untyped memory region. Thus, after this invocation there are no valid references to any object within the untyped region, and the region may be safely retyped and reused.

<sup>1</sup>The treatment of virtual ASIDs imposes a fixed number of address spaces. This limitation is to be removed in future versions of seL4.

<sup>2</sup>Although the CDT conceptually is a separate data structure, it is implemented as part of the CNode object and so requires no additional kernel meta-data.



## Chapter 3

# Capability Spaces

Recall from Section 2.1 that seL4 implements a capability-based access control model. Each userspace thread has an associated *capability space* (CSpace) that contains the capabilities that the thread possesses, thereby governing which resources the thread can access.

Recall that capabilities reside within kernel-managed objects known as CNodes. A CNode is a table of slots, each of which may contain a capability. This may include capabilities to further CNodes, forming a directed graph. Conceptually a thread's CSpace is the portion of the directed graph that is reachable starting with the CNode capability that is its CSpace root.

A CSpace address, also called a CPTR, refers to an individual slot (in some CNode in the CSpace), which may or may not contain a capability. Threads refer to capabilities in their CSpaces (e.g. when making system calls) using the address of the slot that holds the capability in question. An address in a CSpace is the concatenation of the indices of the CNode capabilities forming the path to the destination slot; we discuss this further in Section 3.3.

Recall that capabilities can be copied and moved within CSpaces, and also sent in messages (message sending will be described in detail in Section 4.2.2). Furthermore, new capabilities can be *minted* from old ones with a subset of their rights. Recall, from Section 2.4.1, that seL4 maintains a *capability derivation tree* (CDT) in which it tracks the relationship between these copied capabilities and the originals. The revoke method removes all capabilities (in all CSpaces) that were derived from a selected capability. This mechanism can be used by servers to restore sole authority to an object they have made available to clients, or by managers of Untyped memory to destroy the objects in that memory so it can be retyped.

seL4 requires the programmer to manage all in-kernel data structures, including CSpaces, from userspace. This means that the userspace programmer is responsible for constructing CSpaces as well as addressing capabilities within them. This chapter first discusses capability and CSpace management, before discussing how capabilities are addressed within CSpaces, i.e. how applications can refer to individual capabilities within their CSpaces when invoking methods.

## 3.1 Capability and CSpace Management

### 3.1.1 CSpace Creation

CSpaces are created by creating and manipulating CNode objects. When creating a CNode the user must specify the number of slots that it will have, and this determines the amount of memory that it will use. Each slot requires 16 bytes of physical memory and has the capacity to hold exactly one capability. Like any other object, a CNode must be created by calling `seL4_Untyped_Retype()` on an appropriate amount of untyped memory (see Section 9.3.28). The caller must therefore have a capability to enough untyped memory as well as enough free capability slots available in existing CNodes for the `seL4_Untyped_Retype()` invocation to succeed.

### 3.1.2 CNode Methods

Capabilities are managed largely through invoking CNode methods.

CNodes support the following methods:

`seL4_CNode_Mint()` creates a new capability in a specified CNode slot from an existing capability. The newly created capability may have fewer rights than the original and a different guard (see Section 3.3.1). `seL4_CNode_Mint()` can also create a badged capability (see Section 4.2.1) from an unbadged one.

`seL4_CNode_Copy()` is similar to `seL4_CNode_Mint()`, but the newly created capability has the same badge and data as the original.

`seL4_CNode_Move()` moves a capability between two specified capability slots. You cannot move a capability to the slot in which it is currently.

`seL4_CNode_Mutate()` can move a capability similarly to `seL4_CNode_Move()` and also reduce its rights similarly to `seL4_CNode_Mint()`, although without an original copy remaining.

`seL4_CNode_Rotate()` moves two capabilities between three specified capability slots. It is essentially two `seL4_CNode_Move()` invocations: one from the second specified slot to the first, and one from the third to the second. The first and third specified slots may be the same, in which case the capability in it is swapped with the capability in the second slot. The method is atomic; either both or neither capabilities are moved.

`seL4_CNode_Delete()` removes a capability from the specified slot.

`seL4_CNode_Revoke()` is equivalent to calling `seL4_CNode_Delete()` on each derived child of the specified capability. It has no effect on the capability itself.

`seL4_CNode_SaveCaller()` moves a kernel-generated reply capability of the current thread from the special TCB slot it was created in, into the designated CSpace slot.

`seL4_CNode_Recycle()` is similar to `seL4_CNode_Revoke()`, except that it also resets some aspects of the object to its initial state.

### 3.1.3 Capability Rights

As mentioned previously, some capability types have *access rights* associated with them. Currently, access rights are associated with capabilities for Endpoints, AsyncEPs (see Chapter 4) and Pages (see Chapter 6). The access rights associated with a capability determine the methods that can be invoked. seL4 supports three orthogonal access rights, which are Read, Write and Grant. The meaning of each right is interpreted relative to the various object types, as detailed in Table 3.1.

When an object is first created, the initial capability that refers to it carries the maximum set of access rights. Other, less-powerful capabilities may be manufactured from this original capability, using methods such as `seL4_CNode_Mint()` and `seL4_CNode_Mutate()`. If a greater set of rights than the source capability is specified for the destination capability in either of these invocations, the destination rights are silently downgraded to those of the source.

Type	Read	Write	Grant
Endpoint	Required to wait.	Required to send.	Required to send capabilities (including reply capabilities).
AsyncEP	Required to wait.	Required to send.	N/A
Page	Required to map the page readable.	Required to map the page writable.	N/A

**Table 3.1:** seL4 access rights.

### 3.1.4 Capability Derivation Tree

As mentioned in Section 2.4.1, seL4 keeps track of capability derivations in a capability derivation tree.

Various methods, such as `seL4_CNode_Copy()` or `seL4_CNode_Mint()`, may be used to create derived capabilities. Not all capabilities support derivation. In general, only *original* capabilities support derivation invocations, but there are exceptions. Table 3.2 summarises the conditions that must be met for capability derivation to succeed for the various capability types, and how capability-derivation failures are reported in each case. The capability types not listed can be derived once.

Figure 3.1 shows an example capability derivation tree that illustrates a standard scenario: the top level is a large untyped capability, the second level splits this capability into two regions covered by their own untyped caps, both are children of the first level. The third level on the left is a copy of the level 2 untyped capability. Untyped capabilities when copied always create children, never siblings. In this scenario, the untyped capability was typed into two separate objects, creating two capabilities on level 4, both are the original capability to the respective object, both are children of the untyped capability they were created from.

Ordinary original capabilities can have one level of derived capabilities. Further copies of these derived capabilities will create siblings, in this case remaining on level 5. There is an exception to this scheme for endpoint capabilities — they support an additional layer of depth with the concept of badged and unbadged endpoints. The original

Cap Type	Conditions for Derivation	Error Code on Derivation Failure
ReplyCap	Cannot be derived	Dependent on syscall
IRQControl	Cannot be derived	Dependent on syscall
Untyped	Must not have children (Section 3.2)	<code>seL4_RevokeFirst</code>
Page Table	Must be mapped	<code>seL4_IllegalOperation</code>
Page Directory	Must be mapped	<code>seL4_IllegalOperation</code>
IO Page Table (IA-32 only)	Must be mapped	<code>seL4_IllegalOperation</code>

Table 3.2: Capability Derivation




Figure 3.1: Example capability derivation tree.

endpoint capability will be unbadged. Using the mint method, a copy of the capability with a specific badge can be created. This new, badged capability to the same object is treated as an original capability (the “original badged endpoint capability”) and supports one level of derived children like other capabilities.

## 3.2 Deletion, Revocation, and Recycling

Capabilities in seL4 can be deleted and revoked. Both methods primarily affect capabilities, but they can have side effects on objects in the system.

As described above, `seL4_CNode_Delete()` will remove a capability from the specified CNode slot. Usually, this is all that happens. If, however, it was the last typed capability to an object, this object will now be destroyed by the kernel, cleaning up all remaining references in the kernel to it and preparing the memory for re-use. If the object was a capability container, i.e. a TCB or CNode, the destruction process will recursively delete these capabilities and potentially trigger further destroy operations if some of these capabilities were the last to a specific object.

The `seL4_CNode_Revoke()` method will `seL4_CNode_Delete()` all CDT children of the

specified capability, but will leave the capability itself intact. If any of the revoked child capabilities were the last capabilities to an object, the appropriate destroy operation is triggered.

The `seL4_CNode_Recycle()` method can be used to partially reset an object without fully removing all capabilities to it. Invoking it will first revoke all child capabilities, but it will not remove siblings or parents. Only if, after revocation, the capability is the last typed capability to the object, the same destroy operation as in `seL4_CNode_Delete()` will be executed. Otherwise, not all aspects of the object will be reset: for badged endpoint capabilities, only IPC with this badge will be cancelled in the endpoint, for TCBs the capabilities will be reset, for CNodes, the guard on the capability will be reset. A page will only be cleared, not unmapped.

Note that for page tables and page directories, neither `seL4_CNode_Revoke()` nor `seL4_CNode_Recycle()` will revoke frame capabilities mapped into the address space. They will only be unmapped from the space.

### 3.3 CSpace Addressing


When performing a system call, a thread specifies to the kernel the capability to be invoked by giving an address in its CSpace. This address refers to the specific slot in the caller's CSpace that contains the capability to be invoked.

CSpaces are designed to permit sparsity, and the process of looking-up a capability address must be efficient. Therefore, CSpaces are implemented as *guarded page tables*. As explained earlier, a CSpace is simply a hierarchy of CNode objects, and each CNode is simply a table of slots that each contain either a capability or a reference to another CNode. The kernel stores a capability to the root CNode of each thread's CSpace in the thread's TCB. Conceptually, a CNode capability stores not only a reference to the CNode to which it refers, but also carries two values, its *guard* and *radix*.

#### 3.3.1 Capability Address Lookup

Like a virtual memory address, a capability address is simply an integer. Rather than referring to a location of physical memory (as does a virtual memory address), a capability address refers to a capability slot. When looking up a capability address presented by a userspace thread, the kernel first consults the CNode capability in the thread's TCB that defines the root of the thread's CSpace. It then compares that CNode's *guard* value against the most significant bits of the capability address. If the two values are different, lookup fails. Otherwise, the kernel then uses the next most-significant *radix* bits of the capability address as an index into the CNode to which the CNode capability refers. The slot *s* identified by these next *radix* bits might contain another CNode capability or contain something else (including nothing). If *s* contains a CNode capability *c* and there are remaining bits (following the *radix* bits) in the capability address that have yet to be translated, the lookup process repeats, starting from the CNode capability *c* and using these remaining bits of the capability address. Otherwise, the lookup process terminates successfully; the capability address in question refers to the capability slot *s*.

Figure 3.2 demonstrates a valid CSpace with the following features:



**Figure 3.2:** An example CSpace demonstrating object references at all levels, various guard and radix sizes and internal CNode references.

- a top level CNode object with a 12-bit guard set to 0x000 and 256 slots;
- a top level CNode with direct object references;
- a top level CNode with two second-level CNode references;
- second level CNodes with different guards and slot counts;
- a second level CNode that contains a reference to a top level CNode;
- a second level CNode that contains a reference to another CNode where there are some bits remaining to be translated;
- a second level CNode that contains a reference to another CNode where there are no bits remaining to be translated; and
- object references in the second level CNodes.

It should be noted that Figure 3.2 demonstrates only what is possible, not what is usually practical. Although the CSpace is legal, it would be reasonably difficult to work with due to the small number of slots and the circular references within it.

### 3.3.2 Addressing Capabilities

A capability address is stored in a CPointer (abbreviated CPTR), which is an unsigned integer variable. Capabilities are addressed in accordance with the translation



5.

**L2 CNode Cap.** Recall that to address a CNode capability, the user must supply not only a capability address but also specify the depth limit, which is the maximum number of bits to be translated. L2 CNode Cap resides at offset 0x0F of the first CNode, which has a 4-bit guard of 0x0. Hence, its address is 0x00F00000, with a depth limit of 12 bits.

**L3 CNode Cap.** This capability resides at index 0x00 of the second CNode, which is reached by the L2 CNode Cap. The second CNode has a 4-bit guard of 0x0. Hence, the capability's address is 0x00F00000 with a depth limit of 24 bits. Note that the addresses of the L2 and L3 CNode Caps are the same, but that their depth limits are different.

In summary, to refer to any capability (or slot) in a CSpace, the user must supply its address. When the capability might be a CNode, the user must also supply a depth limit. To specify a range of capability slots, the user supplies a starting address and a window size.

### 3.4 Lookup Failure Description

When a capability lookup fails, a description of the failure is given to either the calling thread or the thread's exception handler in its IPC buffer. The format of the description is always the same but may occur at varying offsets in the IPC buffer depending on how the error occurred. The description format is explained below. The first word indicates the type of lookup failure and the meaning of later words depend on this.

#### 3.4.1 Invalid Root

A CSpace CPTR root (within which a capability was to be looked up) is invalid. For example, the capability is not a CNode cap.

Data	Meaning
Offset + 0	seL4.InvalidRoot

#### 3.4.2 Missing Capability

A capability required for an invocation is not present or does not have sufficient rights.

Data	Meaning
Offset + 0	seL4.MissingCapability
Offset + 1	Bits left



### 3.4.3 Depth Mismatch

When resolving a capability, a CNode was traversed that resolved more bits than was left to decode in the CPTR or a non-CNode capability was encountered while there were still bits remaining to be looked up.

Data	Meaning
Offset + 0	seL4_DepthMismatch
Offset + 1	Bits of CPTR remaining to decode
Offset + 2	Bits that the current CNode being traversed resolved

### 3.4.4 Guard Mismatch

When resolving a capability, a CNode was traversed with a guard size larger than the number of bits remaining or the CNode's guard did not match the next bits of the CPTR being resolved.

Data	Meaning
Offset + 0	seL4_GuardMismatch
Offset + 1	Bits of CPTR remaining to decode
Offset + 2	The CNode's guard
Offset + 3	The CNode's guard size

## Chapter 4

# Inter-process Communication

The seL4 microkernel provides a message-passing mechanism for communication between threads. The mechanism is also used for communication with kernel-provided services. Messages are sent by invoking a capability to a kernel object. Messages sent to *synchronous* (Endpoint) and *asynchronous* (AsyncEP) IPC endpoints are destined for other threads; messages sent to objects of other types are processed by the kernel. This chapter describes the common message format, the two types of endpoints, and how they can be used for communication between applications.

### 4.1 Message Registers

Each message contains a number of message words and optionally a number of capabilities. The message words are sent to or received from a thread by placing them in its *message registers*. The message registers are numbered and the first few message registers are implemented using physical CPU registers, while the rest are backed by a fixed region of memory called the *IPC buffer*. The reason for this design is efficiency: very short messages need not to use the memory. The physical CPU registers used for the message registers are described in Table 4.1 for x86 and Table 4.2 for ARM. The IPC buffer is assigned to the calling thread (see Section 5.1 and Section 9.3.22).

Role	CPU Register
Capability register ( <i>in</i> )	<b>ebx</b>
Badge register ( <i>out</i> )	<b>ebx</b>
Message tag ( <i>in/out</i> )	<b>esi</b>
Message register 1 ( <i>in/out</i> )	<b>edi</b>
Message register 2 ( <i>in/out</i> )	<b>ebp</b>

**Table 4.1:** Physical register allocation for IPC messages on the x86 architecture.

Every IPC message also has a tag (structure `seL4_MessageInfo`). The tag consists of four fields: the label, message length, number of capabilities (the `extraCaps` field) and the `capsUnwrapped` field. The message length and number of capabilities determine either the number of message registers and capabilities that the sending thread wishes

Role	CPU Register
Capability register ( <i>in</i> )	r0
Badge register ( <i>out</i> )	r0
Message tag ( <i>in/out</i> )	r1
Message register 1–4 ( <i>in/out</i> )	r2 – r5

**Table 4.2:** Physical register allocation for IPC messages on the ARM architecture.

to transfer, or the number of message registers and capabilities that were actually transferred. The label is not interpreted by the kernel and is passed unmodified as the first data payload of the message. The label may, for example, be used to specify a requested operation. The `capsUnwrapped` field is used only on the receive side, to indicate the manner in which capabilities were received. It is described in Section 4.2.2.

Type	Name	Description
<code>seL4_MessageInfo</code>	<code>tag</code>	Message tag
<code>seL4_Word[]</code>	<code>msg</code>	Message contents
<code>seL4_Word</code>	<code>reserved</code>	Reserved
<code>seL4_CPtr[]</code> ( <i>in</i> )	<code>caps</code>	Capabilities to transfer
<code>seL4_CapData[]</code> ( <i>out</i> )	<code>badges</code>	Badges for endpoint capabilities received
<code>seL4_CPtr</code>	<code>receiveCNode</code>	CPTR to a CNode from which to find the receive slot
<code>seL4_CPtr</code>	<code>receiveIndex</code>	CPTR to the receive slot relative to <code>receiveCNode</code>
<code>seL4_Word</code>	<code>receiveDepth</code>	Number of bits of <code>receiveIndex</code> to use

**Table 4.3:** Fields of the `seL4_IPCBuffer` structure. Note that `badges` and `caps` use the same area of memory in the structure.

The kernel assumes that the IPC buffer contains a structure of type `seL4_IPCBuffer` as defined in Table 4.3. The kernel uses as many physical registers as possible to transfer IPC messages. When more arguments are transferred than physical message registers are available, the kernel begins using the IPC buffer’s `msg` field to transfer arguments. However, it leaves room in this array for the physical message registers. For example, if an IPC transfer or kernel object invocation required 4 message registers (and there are only 2 physical message registers available on this architecture) then arguments 1 and 2 would be transferred via message registers and arguments 3 and 4 would be in `msg[2]` and `msg[3]`. This allows the user-level object-invocation stubs to copy the arguments passed in physical registers to the space left in the `msg` array if desired. The situation is similar for the tag field. There is space for this field in the `seL4_IPCBuffer` structure, which the kernel ignores. User level stubs may wish to copy the message tag from its CPU register to this field, although the user level stubs provided with the kernel do not do this.

## 4.2 Synchronous Endpoints

Synchronous endpoints (or simply Endpoints) allow a small amount of data and small number of capabilities (namely the IPC buffer) to be transferred between two threads. Endpoints are called ‘synchronous’ because a message transfer will not take place until both the sender is ready to send the message and a receiver is ready to receive it.

Endpoint objects are invoked directly using the seL4 system calls described in Section 2.2. Note that Endpoint objects may queue threads either to send or to receive. If no receiver is ready, threads performing the `seL4_Send()` or `seL4_Call()` system calls will wait in a queue for the first available receiver. Likewise if no sender is ready, threads performing the `seL4_Wait()` system call or the second half of `seL4_ReplyWait()` will wait for the first available sender.

### 4.2.1 Endpoint Badges

Synchronous endpoint capabilities may be *minted* to create a new endpoint capability with a *badge* attached to it. The badge is a word of data that is associated with a particular endpoint capability. When a message is sent to an endpoint using a badged capability, the badge is transferred to the receiving thread’s `badge` register.

An endpoint capability with a zero badge is said to be *unbadged*. Such a capability can be badged with the `seL4_CNode_Mutate()` or `seL4_CNode_Mint()` invocations on the CNode containing the capability. Endpoint capabilities with badges cannot be unbadged, rebadged or used to create child capabilities with different badges.

### 4.2.2 Capability Transfer

Messages in seL4 may contain capabilities. Messages containing capabilities can be sent across synchronous endpoints, provided that the endpoint capability invoked by the sending thread has Grant rights. An attempt to transfer capabilities without Grant rights can still result in the message being sent, but no capabilities will be transferred. Capabilities to be sent with a message are specified in the sending thread’s IPC buffer in the `caps` field. Each entry in that array is interpreted as a CPTR in the sending thread’s capability space. The number of capabilities to send is specified in the `extraCaps` field of the message tag.

The receiver specifies the slot, in which it is willing to receive a capability, with three fields within the IPC buffer: `receiveCNode`, `receiveIndex` and `receiveDepth`. These fields specify the root CNode, capability address and number of bits to resolve, respectively, to find the slot in which to put the capability. Capability addressing is described in Section 3.3.2.

A received capability has the same rights as the original except if the receiving endpoint capability does not have the Write right. In this case, the rights on the sent capability are *diminished*, by removing from the received copy of that capability the Write right. Note that receiving threads may specify only one receive slot, whereas a sending thread may include multiple capabilities in the message. Messages containing more than one capability may be interpreted by kernel objects. They may also be sent to receiving threads in the case where some of the extra capabilities in the message can be *unwrapped*.

If the *n*-th capability in the message refers to the same endpoint as the one the message is being sent through, it is *unwrapped*. Its badge is placed in the *n*-th position of the receiver's badges array and the *n*-th bit (counting from the least significant) is set in the `capsUnwrapped` field of the message tag. The capability itself is not transferred, so the receive slot may be used for another one.

If a receiver gets a message whose tag has an `extraCaps` of 2 and a `capsUnwrapped` of 2, then the first capability in the message was transferred to the specified receive slot and the second capability was unwrapped, placing its badge in `badges[1]`. There may have been a third capability in the sender's message which could not be unwrapped.

### 4.2.3 Errors

Errors in capability transfers can occur at two places: in the send phase or in the receive phase. In the send phase, all capabilities that the caller is attempting to send are looked up to ensure that they exist before the send is initiated in the kernel. If the lookup fails for any reason, `seL4_Send()` and `seL4_Call()` system calls immediately abort and no IPC or capability transfer takes place. The system call will return a lookup failure error as described in Section 9.1.

In the receive phase, `seL4` transfers capabilities in the order that they are found in the sending thread's IPC buffer `caps` array and terminates as soon as an error is encountered. Possible error conditions are:

- A source capability cannot be looked up. Although the presence of the source capabilities is checked when the sending thread performs the send system call, this error may still occur. The sending thread may have been blocked on the endpoint for some time before it was paired with a receiving thread. During this time, its CSpace may have changed and the source capability pointers may no longer be valid.
- The destination slot cannot be looked up. Unlike the send system call, the `seL4_Wait()` system call does not check that the destination slot exists and is empty before it initiates the wait. Hence, the `seL4_Wait()` system call will not fail with an error if the destination slot is invalid and will instead transfer badged capabilities until an attempt to save a capability to the destination slot is made.
- The capability being transferred cannot be derived. See Section 3.1.4 for details.

An error will not void the entire transfer, it will just end it prematurely. The capabilities processed before the failure are still transferred and the `extraCaps` field in the receiver's IPC buffer is set to the number of capabilities transferred up to failure. No error message will be returned to the receiving thread in any of the above cases.

## 4.3 Asynchronous Endpoints

Asynchronous endpoints (AsyncEPs) allow senders to perform IPC without blocking. However, capabilities cannot be transferred over asynchronous endpoints.

Each asynchronous endpoint stores a single word of data. This word of data may be written to using `seL4_Notify()`, causing the first message register of the sending thread to be bitwise or-ed with the asynchronous endpoint's data word.

Note that `seL4_Notify()` is not a proper system call known by the kernel. Rather, it is a convenience wrapper provided by the seL4 userland library which calls `seL4_Send()` with a single parameter. It is useful for notifying an asynchronous endpoint.

Additionally, the `seL4_Wait()` system call may be used with an asynchronous endpoint, allowing the calling thread to retrieve all set bits from the asynchronous endpoint and clearing the endpoint in the process. If no `seL4_Notify()` system calls have taken place since the last `seL4_Wait()` call, the calling thread will block until the next `seL4_Notify()` takes place.

An asynchronous endpoint is the only object that may have `seL4_Poll()` used on it. If a message was received then the label field of the `seL4_MessageInfo` structure will be `seL4_Interrupt`.

### 4.3.1 Asynchronous Endpoint Badges

Like synchronous endpoints, asynchronous endpoint capabilities may also be minted to create a new capability with a *badge* attached to it (see Section 4.2.1). The badge is a word of data that is associated with a particular endpoint capability. When a message is sent to an endpoint using a badged capability, the badge becomes part of the message received: in particular, the badge is bitwise or-ed with the badges from previous send system calls that have occurred since that last receive on the endpoint. Like synchronous endpoints, an asynchronous endpoint capability with a zero badge is said to be *unbadged*. Such a capability can be badged with the `seL4_CNode_Mutate()` or `seL4_CNode_Mint()` invocations on the CNode containing the capability. Asynchronous endpoint capabilities with badges cannot be unbadged, rebadged or used to create child capabilities with different badges.

### 4.3.2 Binding Asynchronous Endpoints

AsyncEP and TCBs can be bound together in a 1-to-1 relationship through the `seL4_TCB_BindAEP()` invocation. When an AsyncEP is bound to a TCB, then messages to that asynchronous endpoint will be delivered if the thread is waiting on any synchronous endpoint. The delivery will occur as if the thread had waited on the asynchronous endpoint, with the label field of the `seL4_MessageInfo` structure set to `seL4_Interrupt`. Once an asynchronous endpoint has been bound, the only thread that may perform `seL4_Wait()` on the endpoint is the bound thread.

# Chapter 5

## Threads and Execution

### 5.1 Threads

seL4 provides threads to represent an execution context and manage processor time. A thread is represented in seL4 by its thread control block object (TCB). Each TCB has an associated CSpace (see Chapter 3) and VSpace (see Chapter 6) which may be shared with other threads. A TCB may also have an IPC buffer (see Chapter 4), which is used to pass extra arguments during IPC or kernel object invocation that do not fit in the architecture-defined message registers. While it is not compulsory that a thread has an IPC buffer, it will not be able to perform most kernel invocations, as they require cap transfer, and can only send short IPCs that fit completely in registers.

#### 5.1.1 Thread Creation

Like other objects, TCBs are created with the `seL4_Untyped_Retype()` method (see Section 2.4). A newly created thread is initially inactive. It is configured by setting its CSpace and VSpace with the `seL4_TCB_SetSpace()` or `seL4_TCB_Configure()` methods and then calling `seL4_TCB_WriteRegisters()` with an initial stack pointer and instruction pointer. The thread can then be activated either by setting the `resume_target` parameter in the `seL4_TCB_WriteRegisters()` invocation to true or by separately calling the `seL4_TCB_Resume()` method.

#### 5.1.2 Thread Deactivation

The `seL4_TCB_Suspend()` method deactivates a thread. A suspended thread might be left as-is, in which case it can later be resumed, and its suspended state can be retrieved with the `seL4_TCB_ReadRegisters()` and `seL4_TCB_CopyRegisters()` methods. It can also be reconfigured and reused or left suspended indefinitely if not needed. Threads will be automatically suspended when the last capability to their TCB is deleted.

#### 5.1.3 Scheduling

seL4 uses a preemptive round-robin scheduler with 256 priority levels. When a thread creates or modifies another thread, it can only set the other thread's priority to be

lower than or equal to its own. Thread priority can be set with `seL4_TCB_Configure()` and `seL4_TCB_SetPriority()` methods.

#### 5.1.4 Exceptions

Each thread has an associated exception-handler endpoint. If the thread causes an exception, the kernel creates an IPC message with the relevant details and forwards this to a thread waiting on the endpoint. This thread can then take the appropriate action. Fault IPC messages are described in Section 5.2.

In order to enable exception handlers a capability to the exception-handler endpoint must exist in the CSpace of the thread that generates the exception. The exception-handler endpoint can be set with the `seL4_TCB_SetSpace()` or `seL4_TCB_Configure()` method. With these methods, a capability address for the exception handler can be associated with a thread. This address is then used to lookup the handler endpoint when an exception is generated. Note, however, that these methods make no attempt to check whether an endpoint capability exists at the specified address in the CSpace of the thread. The capability is only looked up when an exception actually happens and if the lookup fails then no exception message is delivered and the thread is suspended indefinitely.

The exception endpoint must have send and grant rights. Replying to the IPC restarts the thread. For certain exception types, the contents of the reply message may be used to set the values in the registers of the thread being restarted. See Section 5.2 for details.

#### 5.1.5 Message Layout of the Read-/Write-Registers Methods

The registers of a thread can be read and written with the `seL4_TCB_ReadRegisters()` and `seL4_TCB_WriteRegisters()` methods. The register contents are transferred via the IPC buffer. The IPC buffer locations that registers are copied to/from are given below.

#### IA-32

Register	IPC Buffer location
EIP	IPCBuffer [0]
ESP	IPCBuffer [1]
EFLAGS	IPCBuffer [2]
EAX	IPCBuffer [3]
EBX	IPCBuffer [4]
ECX	IPCBuffer [5]
EDX	IPCBuffer [6]
ESI	IPCBuffer [7]
EDI	IPCBuffer [8]
EBP	IPCBuffer [9]
TLS_BASE	IPCBuffer [10]
FS	IPCBuffer [11]
GS	IPCBuffer [12]



**ARM**

Register	IPC Buffer location
FaultInstruction	IPCBuffer[0]
SP	IPCBuffer[1]
CPSR	IPCBuffer[2]
R0-R1	IPCBuffer[3-4]
R8-R12	IPCBuffer[5-9]
R2-R7	IPCBuffer[10-15]
R14	IPCBuffer[16]

**5.2 Faults**

A thread's actions may result in a fault. Faults are delivered to the thread's exception handler so that it can take the appropriate action. The fault type is specified in the message label and is one of: `seL4_CapFault`, `seL4_VMFault`, `seL4_UnknownSyscall`, `seL4_UserException` or `seL4_Interrupt`.

**5.2.1 Capability Faults**

Capability faults may occur in two places. Firstly, a capability fault can occur when lookup of a capability referenced by a `seL4_Call()` or `seL4_Send()` system call failed (`seL4_NBSend()` calls on invalid capabilities silently fail). In this case, the capability on which the fault occurred may be the capability being invoked or an extra capability passed in the `caps` field in the IPC buffer.

Secondly, a capability fault can occur when `seL4.Wait()` is called on a capability that does not exist, is not an endpoint capability or does not have receive permissions.

Replying to the fault IPC will restart the faulting thread. The contents of the IPC message are given in Table 5.1.

Meaning	IPC buffer Location
Program counter to restart execution at	IPCBuffer[0]
Capability address	IPCBuffer[1]
In receive phase (1 if the fault happened during a wait system call, 0 otherwise)	IPCBuffer[2]
Lookup failure description. As described in Section 3.4	IPCBuffer[3..]

**Table 5.1:** Contents of an IPC message.

**5.2.2 Unknown Syscall**

This fault occurs when a thread executes a system call with a syscall number that is unknown to seL4. The register set of the faulting thread is passed to the thread's

exception handler so that it may, for example, emulate the system call if a thread is being virtualised.

Replying to the fault IPC allows the thread to be restarted and/or the thread's register set to be modified. If the reply has a label of zero, the thread will be restarted. Additionally, if the message length is non-zero, the faulting thread's register set will be updated as shown in Table 5.2 and Table 5.3. In this case, the number of registers updated is controlled with the length field of the message tag.

## ARM

Value sent	Register set by reply	IPC buffer location
R0-R7	(same)	IPCBuffer [0-7]
FaultInstruction	(same)	IPCBuffer [8]
SP	(same)	IPCBuffer [9]
LR	(same)	IPCBuffer [10]
CPSR	(same)	IPCBuffer [11]
Syscall number	—	IPCBuffer [12]

**Table 5.2:** Unknown system call outcome on the ARM architecture.

## IA-32

Value sent	Register set by reply	IPC buffer location
EAX	(same)	IPCBuffer [0]
EBX	(same)	IPCBuffer [1]
ECX	(same)	IPCBuffer [2]
EDX	(same)	IPCBuffer [3]
ESI	(same)	IPCBuffer [4]
EDI	(same)	IPCBuffer [5]
EBP	(same)	IPCBuffer [6]
ESP	(same)	IPCBuffer [7]
EFLAGS	(same)	IPCBuffer [8]
Syscall number	—	IPCBuffer [9]

**Table 5.3:** Unknown system call outcome on the IA-32 architecture.

### 5.2.3 User Exception

User exceptions are used to deliver architecture-defined exceptions. For example, such an exception could occur if a user thread attempted to divide a number by zero.

Replying to the fault IPC allows the thread to be restarted and/or the thread's register set to be modified. If the reply has a label of zero, the thread will be restarted. Additionally, if the message length is non-zero, the faulting thread's register set will be updated as shown in Table 5.4 and Table 5.5. In this case, the number of registers updated is controlled with the length field of the message tag.

**ARM**

Value sent	Register set by reply	IPC buffer location
FaultInstruction	(same)	IPCBuffer[0]
SP	(same)	IPCBuffer[1]
CPSR	(same)	IPCBuffer[2]
Exception number	—	IPCBuffer[3]
Exception code	—	IPCBuffer[4]

**Table 5.4:** User exception outcome on the ARM architecture.**IA-32**

Value sent	Register set by reply	IPC buffer location
EIP	(same)	IPCBuffer[0]
ESP	(same)	IPCBuffer[1]
EFLAGS	(same)	IPCBuffer[2]
Exception number	—	IPCBuffer[3]
Exception code	—	IPCBuffer[4]

**Table 5.5:** User exception outcome on the IA-32 architecture.**5.2.4 VM Fault**

The thread caused a page fault. Replying to the fault IPC will restart the thread. The contents of the IPC message are given below.

Meaning	IPC buffer location
Program counter to restart execution at.	IPCBuffer[0]
Address that caused the fault.	IPCBuffer[1]
Instruction fault (1 if the fault was caused by an instruction fetch).	IPCBuffer[2]
Fault status register (FSR). Contains information about the cause of the fault.	IPCBuffer[3]
Architecture dependent.	

## Chapter 6

# Address Spaces and Virtual Memory

A virtual address space in seL4 is called a VSpace. In a similar way to a CSpace (see Chapter 3), a VSpace is composed of objects provided by the microkernel. Unlike CSpaces, these objects for managing virtual memory largely correspond to those of the hardware; that is, a page directory pointing to page tables, which in turn map physical frames. The kernel also includes ASID Pool and ASID Control objects for tracking the status of address spaces.

These VSpace-related objects are sufficient to implement the hardware data structures required to create, manipulate, and destroy virtual memory address spaces. It should be noted that, as usual, the manipulator of a virtual memory space needs the appropriate capabilities to the required objects.

### 6.1 Overview

**IA-32** IA-32 processors have a two-level page-table structure. The top-level page directory covers a 4 GiB range and each page table covers a 4 MiB range. Frames can be 4 KiB or 4 MiB. Before a 4 KiB frame can be mapped, a page table covering the range that the frame will be mapped into must have been mapped, otherwise seL4 will return an error. 4 MiB frames are mapped directly into the page directory, thus, a page table does not need to be mapped first.

**ARM** ARM processors also have a two-level page-table structure. The top-level page directory covers a range of 4 GiB and each page table covers a 1 MiB range. Four page sizes are allowed: 4 KiB, 64 KiB, 1 MiB and 16 MiB. 4 KiB and 16 KiB pages are mapped into the second-level page table. Before they can be mapped, a page table covering the range that they will be mapped into must have been installed. 1 MiB and 16 MiB pages are installed directly into the page directory such that it is not necessary to map a page table first. Pages of 4 KiB and 1 MiB size occupy one slot in a page table and the page directory, respectively. Pages of 64 KiB and 16 MiB size occupy 16 slots in a page table and the page directory, respectively.

## 6.2 Objects

**Page Directory** The Page Directory (PD) is the top-level page table of the two-level page table structure. It has a hardware-defined format, but conceptually contains a number of page directory entries (PDEs). The Page Directory has no methods itself, but it is used as an argument to several other virtual-memory related object invocations.

**Page Table** The Page Table object forms the second level of the page-table structure. It contains a number of slots, each of which contains a page-table entry (PTE).

Page Table objects possess only a single method:

`seL4_ARM_PageTable_Map()`

`seL4_IA32_PageTable_Map()`

Takes a Page Directory capability as an argument, and installs a reference to the invoked Page Table in a specified slot in the Page Directory.

**Page** A Page object is a region of physical memory that is used to implement virtual memory pages in a virtual address space. The Page object has the following methods:

`seL4_ARM_Page_Map()`

`seL4_IA32_Page_Map()`

Takes a Page Directory or a Page Table capability as an argument and installs a PDE or PTE referring to the Page in the specified location, respectively.

`seL4_ARM_Page_Remap()`

`seL4_IA32_Page_Remap()`

Changes the permissions of an existing mapping.

`seL4_ARM_Page_Unmap()`

`seL4_IA32_Page_Unmap()`

Removes an existing mapping.

The virtual address for a Page mapping must be aligned to the size of the Page. To map a page readable, the capability to the page that is being invoked must have read permissions. To map the page writable, the capability must have write permissions. The requested mapping permissions are specified with an argument of type `seL4_CapRights` given to the `seL4_ARM_Page_Map()` or `seL4_IA32_Page_Map()` method. `seL4_CanRead` and `seL4_CanWrite` are the only valid permissions on both ARM and IA-32 architectures. If the capability does not have sufficient permissions to authorise the given mapping, then the mapping permissions are silently downgraded.

**ASID Control** For internal kernel book-keeping purposes, there is a fixed maximum number of applications the system can support. In order to manage this limited resource, the microkernel provides an ASID Control capability. The ASID Control capability is used to generate a capability that authorises the use of a subset of available address-space identifiers. This newly created capability is called an ASID Pool. ASID Control only has a single method:

```
seL4_ARM_ASIDControl_MakePool()
seL4_IA32_ASIDControl_MakePool()
```

Together with a capability to Untyped Memory as argument creates an ASID Pool.

The untyped capability given to the `seL4_ARM_ASIDControl_MakePool()` call must represent a 4K memory object. This will create an ASID pool with enough space for 1024 VSpaces.

**ASID Pool** An ASID Pool confers the right to create a subset of the available maximum applications. For a VSpace to be usable by an application, it must be assigned to an ASID. This is done using a capability to an ASID Pool. The ASID Pool object has a single method:

```
seL4_ARM_ASIDPool_Assign()
seL4_IA32_ASIDPool_Assign()
```

Assigns an ASID to the VSpace associated with the Page Directory passed in as an argument.

### 6.3 Mapping Attributes

A parameter of type `seL4_ARM_VMAAttributes` or `seL4_IA32_VMAAttributes` is used to specify the cache behavior of the page being mapped; possible values for ARM are shown in Table 6.1 and values for IA-32 are shown in Table 6.2.

Attribute	Meaning
<code>seL4_ARM_PageCacheable</code>	Enable data in this mapping to be cached
<code>seL4_ARM_ParityEnabled</code>	Enable parity checking for this mapping

**Table 6.1:** Virtual memory attributes for ARM page table entries.

Attribute	Meaning
<code>seL4_IA32_CacheDisabled</code>	Prevent data in this mapping from being cached
<code>seL4_IA32_WriteThrough</code>	Enable write through cacheing for this mapping

**Table 6.2:** Virtual memory attributes for IA32 page table entries.

### 6.4 Sharing Memory

seL4 does not allow Page Tables to be shared, but does allow pages to be shared between address spaces. To share a page, the capability to the Page must first be duplicated using the `seL4_CNode_Copy()` method and the new copy must be used in the `seL4_ARM_Page_Map()` or `seL4_IA32_Page_Map()` method that maps the page into the second address space. Attempting to map the same capability twice will result in an error.

## 6.5 Page Faults

Page faults are reported to the exception handler of the executed thread. See Section 5.2.4.

# Chapter 7

## Hardware I/O

### 7.1 Interrupt Delivery

Interrupts are delivered in seL4 through AsyncEP objects. A thread may configure the kernel to send a message to a particular AsyncEP object each time a certain interrupt triggers. Threads may then wait for the interrupts to occur by calling `seL4.Wait()` on that AsyncEP.

IRQHandler capabilities are used to restrict which threads are able to configure individual interrupts. Each IRQHandler allows its holder to configure a single interrupt. It has three methods:

`seL4_IRQHandler_SetEndpoint()` specifies the AsyncEP that the kernel should `notify()` when an interrupt occurs. The caller may also specify the contents of the message to be sent. A driver may then call `seL4.Wait()` on this endpoint to wait for interrupts to arrive.

`seL4_IRQHandler_Ack()` informs the kernel that the userspace driver has finished processing the interrupt and the microkernel can send further pending or new interrupts to the application.

`seL4_IRQHandler_Clear()` de-registers the AsyncEP from the IRQHandler object.

When the system first starts, no IRQHandler capabilities are present. Instead, the initial thread's CSpace contains a single IRQControl capability. This capability may be used to produce a single IRQHandler capability for each interrupt available in the system. Typically, the initial thread of a system will determine which IRQs are required by other components in the system, produce an IRQHandler capability for each interrupt, and then delegate the resulting capabilities as appropriate. IRQControl has one method:

`seL4_IRQControl_Get()` creates an IRQHandler capability for the specified interrupt source.



## 7.2 IA-32-Specific I/O

### 7.2.1 I/O Ports

On IA-32 platforms, seL4 provides access to I/O ports to user-level threads. Access to I/O ports is controlled by IO Port capabilities. Each IO Port capability identifies a range of ports that can be accessed with it. Reading from I/O ports is accomplished with the `seL4_IA32_IOPort_In8()`, `seL4_IA32_IOPort_In16()`, and `seL4_IA32_IOPort_In32()` methods, which allow for reading of 8-, 16- and 32-bit quantities. Similarly, writing to I/O ports is accomplished with the `seL4_IA32_IOPort_Out8()`, `seL4_IA32_IOPort_Out16()`, and `seL4_IA32_IOPort_Out32()` methods. Each of these methods takes as arguments an IO Port capability and an unsigned integer `port`, which indicates the I/O port to read from or write to, respectively. In each case, `port` must be within the range of I/O ports identified by the given IO Port capability in order for the method to succeed.

At system initialisation, the initial thread's CSpace contains the master IO Port capability, which allows access to all I/O ports. Other IO Port capabilities, which authorise access to a specific range of I/O Ports, may be derived from this master capability using the `seL4_CNode_Mint()` method. The range of I/O ports that the newly created capability should identify are specified via the 32-bit `badge` argument provided to `seL4_CNode_Mint()`. The first port number in the range occupies the top 16 bits of `badge`, while the last port number in the range occupies the bottom 16 bits. The range is interpreted as being inclusive of these two numbers.

The I/O port methods return error codes upon failure. A `seL4_IllegalOperation` code is returned if port access is attempted outside the range allowed by the IO Port capability. Since invocations that read from I/O ports are required to return two values – the value read and the error code – a structure containing both values is returned from the API call.

### 7.2.2 I/O Space

I/O devices capable of DMA present a security risk because the CPU's MMU is bypassed when the device accesses memory. In seL4, device drivers run in user space to keep them out of the trusted computing base. A malicious or buggy device driver may, however, program the device to access or corrupt memory that is not part of its address space, thus subverting security. To mitigate this threat, seL4 provides support for the IOMMU on Intel IA-32-based platforms. An IOMMU allows memory to be remapped from the device's point of view. It acts as an MMU for the device, restricting the regions of system memory that it can access. More information can be obtained from Intel's IOMMU documentation [Int08].

seL4-based systems that wish to utilise DMA must have an IOMMU. This restriction results from the fact that seL4 provides no way to obtain the physical address of a Page from its capability. Hence, applications are unable to accurately instruct devices, at which address they should directly address the physical memory. Instead, frames of memory must be mapped into the device's address space using seL4's IOMMU primitives.

Two new objects are provided by the kernel to abstract the IOMMU:

**IOspace** This object represents the address space associated with a hardware device on the PCI bus. It represents the right to modify a device's memory mappings.

**IOPageTable** This object represents a node in the multilevel page-table structure used by IOMMU hardware to translate hardware memory accesses.

Page capabilities are used to represent the actual frames that are mapped into the I/O address space. A Page can be mapped into either a VSpace or an IOspace but never into both at the same time.

IOspace and VSpace fault handling differ significantly. VSpace page faults are redirected to the thread's exception handler (see Section 5.2), which can take the appropriate action and restart the thread at the faulting instruction. There is no concept of an exception handler for an IOspace. Instead, faulting transactions are simply aborted; the device driver must correct the cause of the fault and retry the DMA transaction.

An initial master IOspace capability is provided in the initial thread's CSpace. An IOspace capability for a specific device is created by using the `seL4_CNode_Mint()` method, passing the PCI identifier of the device as the `badge` argument. PCI identifiers are explained fully in the PCI specification [SA99], but are briefly described here. A PCI identifier is a 16-bit quantity. The first 8 bits identify the bus that the device is on. The next 5 bits are the device identifier: the number of the device on the bus. The last 3 bits are the function number. A single device may consist of several independent functions, each of which may be addressed by the PCI identifier.

The IOMMU page-table structure has three levels. Page tables are mapped into an IOspace using the `seL4_IA32_IOPageTable_Map()` method. This method takes the IOPageTable to map, the IOspace to map into and the address to map at. Three levels of page tables must be mapped before a frame can be mapped successfully. A frame is mapped with the `seL4_IA32_Page_MapIO()` method whose parameters are analogous to the corresponding method that maps Pages into VSpaces (see Chapter 6), namely `seL4_IA32_Page_Map()`.

Unmapping is accomplished with the usual `unmap` (see Chapter 6) API call, `seL4_IA32_Page_Unmap()`.

More information about seL4's IOMMU abstractions can be found in [Pal08].

# Chapter 8

## System Bootstrapping

### 8.1 Initial Thread's Environment

The seL4 kernel creates a minimal boot environment for the initial thread. This environment consists of the initial thread's TCB, CSpace and VSpace, consisting of frames that contain the userland image (code/data of the initial thread) and the IPC buffer. The initial thread's CSpace consists of exactly one CNode which contains capabilities to the initial thread's own resources as well as to all available global resources. The CNode size can be configured at compile time (default is  $2^{12}$  slots), but the guard is always chosen so that the CNode resolves exactly 32 bits. This means, the first slot of the CNode has CPTR 0x0, the second slot has CPTR 0x1 etc.

The first 11 slots contain specific capabilities as listed in Table 8.1.

**Table 8.1:** Initial Thread's CNode Content

CPTR	Enum Constant	Capability
0x0	<code>seL4_CapNull</code>	null
0x1	<code>seL4_CapInitThreadTCB</code>	initial thread's TCB
0x2	<code>seL4_CapInitThreadCNode</code>	initial thread's CNode
0x3	<code>seL4_CapInitThreadPD</code>	initial thread's page directory
0x4	<code>seL4_CapIRQControl</code>	global IRQ controller (see Section 7.1)
0x5	<code>seL4_CapASIDControl</code>	global ASID controller (see Chapter 6)
0x6	<code>seL4_CapInitThreadASIDPool</code>	initial thread's ASID pool (see Chapter 6)
0x7	<code>seL4_CapIOPort</code>	global I/O port cap, null cap if unsupported (see Section 7.2.1)
0x8	<code>seL4_CapIOSpace</code>	global I/O space cap, null cap if unsupported (see Section 7.2.2)
0x9	<code>seL4_CapBootInfoFrame</code>	BootInfo frame (see Section 8.2)
0xa	<code>seL4_CapInitThreadIPCBuffer</code>	initial thread's IPC buffer (see Section 4.1)

## 8.2 BootInfo Frame

CNode slots with CPTR 0xb and above are filled dynamically during bootstrapping. Their exact contents depend on the userland image size, platform configuration (devices) etc. In order to tell the initial thread which capabilities are stored where in its CNode, the kernel provides a *BootInfo Frame* which is mapped into the initial thread's address space. The mapped address is chosen by the kernel and given to the initial thread via a CPU register. Usually, the initial thread instruments the seL4 userland library to handle this. The library then provides the mapped address through function `seL4.GetBootInfo()`.

The BootInfo Frame contains the C struct described in Table 8.2. It is defined in the seL4 userland library. Besides talking about capabilities, it also informs the initial thread about the current platform's configuration.

The type `seL4.SlotRegion` is a C struct which contains `start` and `end` slot CPTRs. It denotes a region of slots in the initial thread's CNode, starting with CPTR `start` and with `end` being the CPTR of the first slot after the region ends, i.e. `end - 1` points to the last slot of the region.

**Table 8.2:** BootInfo Struct

Field Type	Field Name	Description
seL4_Word	nodeID	node ID (see Section 8.4)
seL4_Word	numNodes	number of nodes (see Section 8.4)
seL4_Word	numIOPTLevels	number of I/O page-table levels (0 if no IOMMU)
seL4_IPCBuffer*	ipcBuffer	pointer to the initial thread's IPC buffer
seL4_SlotRegion	empty	empty slots (null caps)
seL4_SlotRegion	sharedFrames	see Section 8.4
seL4_SlotRegion	userImageFrames	frames containing the userland image
seL4_SlotRegion	userImagePTs	page tables covering the userland image
seL4_SlotRegion	untyped	untyped-memory capabilities
seL4_Word[]	untypedPaddrList	array of untyped-memory physical addresses
uint8_t[]	untypedSizeBitsList	array of untyped-memory sizes ( $2^n$ bytes)
uint8_t	initThreadCNodeSizeBits	CNode size ( $2^n$ slots)
seL4_Word	numDeviceRegions	number of device memory regions
seL4_DeviceRegion[]	deviceRegions	device memory regions (see Table 8.3)

The capabilities in `userImageFrames` and `userImagePTs` are ordered, i.e. the first

capability references the first frame of the userland image etc. Userland always knows to which virtual addresses its own code and data is mapped (e.g. in GCC, with the standard linker script, the symbols `_start` and `_end` are available). Userland can therefore infer the virtual address behind each userland frame and page-table cap.

Untyped memory is given in no particular order. The array entry `untypedSizeBitList[i]` stores the untyped-memory size ( $2^n$  bytes) of the  $i$ -th untyped cap of the slot region `untyped`. Therefore, the array length is at least `untyped.end - untyped.start`. The actual length is hardcoded in the kernel and irrelevant to the reader of the array. The same is true for the array `untypedPaddrList`. For each untyped-memory capability, it stores the physical addresses backing the untyped memory. This allows userland to infer physical memory addresses of retyped frames and use them to initiate DMA transfers when no IOMMU is available. The kernel makes no guarantees about certain sizes of untyped memory being available except that it provides a compile-time-configurable minimum number of 4K untyped capabilities (default is 12).

**Table 8.3:** DeviceRegion Struct

Field Type	Field Name	Description
seL4_Word	<code>basePaddr</code>	physical base address of the device region
seL4_Word	<code>frameSizeBits</code>	size ( $2^n$ bytes) of the frames used
seL4_SlotRegion	<code>frames</code>	capabilities to the frames covering the region

The kernel creates frames covering each physical memory region associated with a memory-mapped device. These device regions are either hardcoded (e.g. on embedded platforms) or discovered at boot time by the kernel through a PCI bus scan. The physical base address of each region is stored in `basePaddr`. The slot region `frames` identifies all frame caps used to back this region. They are ordered, so the first frame of the region is referenced by the first cap in this slot region and is backed by the physical address `basePaddr`. All frames have the same size:  $2^{\text{frameSizeBits}}$  bytes. Hence, the size of the whole region is: `(frames.end - frames.start) << frameSizeBits`

The array `deviceRegions` of the `BootInfo` struct stores all available device regions (i.e. their structs). There are `numDeviceRegions` of them available in the array.

If the platform has an seL4-supported IOMMU, `numIOPTLevels` contains the number of IOMMU-page-table levels. This information is needed by userland when constructing an IOMMU address space (`IOSpace`). If there is no IOMMU support, `numIOPTLevels` is 0.

## 8.3 Boot Command-line Arguments

On IA-32, seL4 accepts boot command-line arguments which are passed to the kernel via a multiboot-compliant bootloader (e.g. GRUB, syslinux). Multiple arguments are separated from each other by whitespaces. Two forms of arguments are accepted: (1) key-value arguments of the form “key=value” and (2) single keys of the form “key”. The value field of the key-value form may be a string, a decimal integer, a hexadecimal integer beginning with “0x”, or an integer list where list elements are

separated by commas. Keys and values can't have any whitespaces in them and there are no whitespaces before or after an "=" or a comma either. Arguments are listed in Table 8.4 along with their default values (if left unspecified).

**Table 8.4:** IA-32 boot command-line arguments

Key	Value	Default
<code>console_port</code>	I/O-port base of the serial port that the kernel prints to (if compiled in debug mode)	0x3f8
<code>debug_port</code>	I/O-port base of the serial port that is used for capDL dumps (if compiled in debug mode)	0x3f8
<code>disable_iommu</code>	none	The IOMMU is enabled by default on VT-d-capable platforms
<code>max_num_nodes</code>	Maximum number of seL4 nodes that can be started up (see Section 8.4)	1
<code>num_sh_frames</code>	Number of frames shared between seL4 nodes (see Section 8.4)	0

## 8.4 Multikernel Bootstrapping

On ARM, seL4 is uniprocessor only and does not support multikernel [BBD<sup>+</sup>09] bootstrapping. Therefore, the field `nodeID` of the `BootInfo` struct will always be 0, `numNodes` will be 1 and `sharedFrames` will be the empty slot region.

On IA-32, seL4 can be bootstrapped as a multikernel by setting the boot command-line argument `max_num_nodes` to a value >1. Each available CPU core will then run one isolated *node* of seL4, up to the maximum number specified. The available physical memory is partitioned equally between nodes. The assignment of devices to nodes can be configured statically at compile time. By default, all devices (i.e. their memory regions) are assigned to the first node. IOMMU management can only be performed by the first node, the other nodes are not given a global IOSpace capability. There is also a hard upper limit of number of nodes defined at compile time (default is 8, but it can be increased to 256).

Nodes are isolated from each other, except for *shared frames*. When bootstrapping, the kernel creates a number of 4K userland frames which are shared between nodes. This number can be configured via the boot command-line argument `num_sh_frames`. The shared frames will appear in the `CNode` of each node's initial thread. They are given to each initial thread in the same order. In the `BootInfo` struct, the field `sharedFrames` contains their slot region.

Shared frames can be used by userland to implement all sorts of shared data structures, message passing and synchronisation mechanisms. Individual frames can, for example, be minted and handed out to subsystems. This allows connecting them across nodes

in a fine-grained manner. Each node has a node ID (field `nodeID` in `BootInfo`) whereas the number of nodes can be obtained from the field `numNodes`.

Userland images are given to the kernel by a multiboot-compliant bootloader (e.g. GRUB, syslinux) via *boot modules*. Each boot module contains an ELF file of a userland image. If there is only one userland image, each node will get its own copy of that userland image. If multiple userland images are given, the first node gets the first image, the second node the second image etc. If there are more nodes than images, each remaining node gets a copy of the last image.

If the kernel is compiled in debug mode, each node can be assigned a separate console port and debug port (see Table 8.4) which is done by specifying an array of I/O-port base addresses. For example, `console_port=0x3f8,0x2f8,0x3e8,0x2e8` assigns port 0x3f8 to node 0, port 0x2f8 to node 1, etc. The remaining nodes have no assigned port and produce no console output. The argument `debug_port` works in exactly the same way.

Further details can be obtained from [vT10] which mainly talks about the formal aspects of seL4's multikernel version but also contains details about the bootstrapping.

# Chapter 9

## seL4 API Reference

### 9.1 Error Codes

Invoking a capability with invalid parameters will result in an error. seL4 system calls return an error code in the message tag and a short error description in the message registers to aid the programmer in determining the cause of errors.

#### 9.1.1 Invalid Argument

A non-capability argument is invalid.

Field	Meaning
Label	<code>seL4_InvalidArgument</code>
<code>IPCBuffer[0]</code>	Invalid argument number

#### 9.1.2 Invalid Capability

A capability argument is invalid.

Field	Meaning
Label	<code>seL4_InvalidCapability</code>
<code>IPCBuffer[0]</code>	Invalid capability argument number

#### 9.1.3 Illegal Operation

The requested operation is not permitted.

Field	Meaning
Label	<code>seL4_IllegalOperation</code>



### 9.1.4 Range Error

An argument is out of the allowed range.

Field	Meaning
Label	<code>seL4_RangeError</code>
<code>IPCBuffer[0]</code>	Minimum allowed value
<code>IPCBuffer[1]</code>	Maximum allowed value

### 9.1.5 Alignment Error

A supplied argument does not meet the alignment requirements.

Field	Meaning
Label	<code>seL4_AlignmentError</code>

### 9.1.6 Failed Lookup

A capability could not be looked up.

Field	Meaning
Label	<code>seL4_FailedLookup</code>
<code>IPCBuffer[0]</code>	1 if the lookup failed for a source capability, 0 otherwise
<code>IPCBuffer[1]</code>	Type of lookup failure
<code>IPCBuffer[2..]</code>	Lookup failure description as described in Section 3.4

### 9.1.7 Delete First

A destination slot specified in the syscall arguments is occupied.

Field	Meaning
Label	<code>seL4_DeleteFirst</code>

### 9.1.8 Revoke First

The object currently has other objects derived from it and the requested invocation cannot be performed until either these objects are deleted or the revoke invocation is performed on the capability.

Field	Meaning
Label	<code>seL4_RevokeFirst</code>

## 9.2 System Calls

### 9.2.1 Send

```
static inline void sel4_Send
```

Send to a capability

Type	Name	Description
sel4_CPtr	dest	The capability to be invoked.
sel4_MessageInfo	msgInfo	The messageinfo structure for the IPC.

*Return value:* This method does not return anything.

*Description:* See Section 2.2

### 9.2.2 Wait

```
static inline sel4_MessageInfo sel4_Wait
```

Wait on an endpoint

Type	Name	Description
sel4_CPtr	src	The capability to be invoked.
sel4_Word*	sender	The badge of the endpoint capability that was invoked by the sender is written to this address.

*Return value:* A `sel4_MessageInfo` structure as described in Section 4.1.

*Description:* See Section 2.2

### 9.2.3 Call

```
static inline sel4_MessageInfo sel4_Call
```

Call a capability

Type	Name	Description
sel4_CPtr	dest	The capability to be invoked.
sel4_MessageInfo	msgInfo	The messageinfo structure for the IPC.

*Return value:* A `sel4_MessageInfo` structure as described in Section 4.1.

*Description:* See Section 2.2

### 9.2.4 Reply

```
static inline void seL4_Reply
```

Perform a send to a one-off reply capability stored when the thread was last called

Type	Name	Description
seL4_MessageInfo	msgInfo	The messageinfo structure for the IPC.

*Return value:* This method does not return anything.

*Description:* See Section 2.2

### 9.2.5 Non-blocking Send

```
static inline void seL4_NBSend
```

Perform a non-blocking send to a capability

Type	Name	Description
seL4_CPtr	dest	The capability to be invoked.
seL4_MessageInfo	msgInfo	The messageinfo structure for the IPC.

*Return value:* This method does not return anything.

*Description:* See Section 2.2

### 9.2.6 Reply Wait

```
static inline seL4_MessageInfo seL4_ReplyWait
```

Perform a reply followed by a wait in one system call

Type	Name	Description
seL4_CPtr	dest	The capability to be invoked.
seL4_MessageInfo	msgInfo	The messageinfo structure for the IPC.
seL4_Word*	sender	The badge of the endpoint capability that was invoked by the sender is written to this address.

*Return value:* A seL4\_MessageInfo structure as described in Section 4.1.

*Description:* See Section 2.2

### 9.2.7 Poll

```
static inline seL4_MessageInfo seL4_Poll
```

Poll an asynchronous endpoint

Type	Name	Description
seL4_CPtr	src	The capability to be invoked.
seL4_Word*	sender	The badge of the endpoint capability that was invoked by the sender is written to this address.

*Return value:* A `seL4_MessageInfo` structure as described in Section 4.1.

*Description:* See Section 2.2

### 9.2.8 Yield

```
static inline void seL4_Yield
```

Donate the remaining timeslice to a thread of the same priority

Type	Name	Description
void		

*Return value:* This method does not return anything.

*Description:* See Section 2.2

### 9.2.9 Notify

```
static inline void seL4_Notify
```

Send a one-word message

Type	Name	Description
seL4_CPtr	dest	The capability to be invoked.
seL4_Word	msg	The single word to send.

*Return value:* This method does not return anything.

*Description:* This is not a proper system call known by the kernel. Rather, it is a convenience wrapper provided by the seL4 userland library which calls `seL4_Send()` with a single parameter. It is useful for notifying an asynchronous endpoint.

See the description of `seL4_Send()` in Section 2.2

## 9.3 Architecture-Independent Object Methods

### 9.3.1 CNode - Copy

```
static inline int seL4_CNode_Copy
```

Copy a capability, setting its access rights whilst doing so

Type	Name	Description
seL4_CNode	<code>_service</code>	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	<code>dest_index</code>	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	<code>dest_depth</code>	Number of bits of <code>dest_index</code> to resolve to find the destination slot.
seL4_CNode	<code>src_root</code>	CPTR to the CNode that forms the root of the source CSpace. Must be at a depth of 32.
seL4_Word	<code>src_index</code>	CPTR to the source slot. Resolved from the root of the source CSpace.
uint8_t	<code>src_depth</code>	Number of bits of <code>src_index</code> to resolve to find the source slot.
seL4_CapRights	<code>rights</code>	The rights inherited by the new capability. Possible values for this type are given in Section 3.1.3.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.2 CNode - Delete

```
static inline int sel4_CNode_Delete
```

Delete a capability

Type	Name	Description
sel4_CNode	_service	CPTR to the CNode at the root of the CSpace where the capability will be found. Must be at a depth of 32.
sel4_Word	index	CPTR to the capability. Resolved from the root of the _service parameter.
uint8_t	depth	Number of bits of index to resolve to find the capability being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.3 CNode - Mint

```
static inline int seL4_CNode_Mint
```

Copy a capability, setting its access rights and badge whilst doing so

Type	Name	Description
seL4_CNode	_service	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	dest_index	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	dest_depth	Number of bits of dest_index to resolve to find the destination slot.
seL4_CNode	src_root	CPTR to the CNode that forms the root of the source CSpace. Must be at a depth of 32.
seL4_Word	src_index	CPTR to the source slot. Resolved from the root of the source CSpace.
uint8_t	src_depth	Number of bits of src_index to resolve to find the source slot.
seL4_CapRights	rights	The rights inherited by the new capability. Possible values for this type are given in Section 3.1.3.
seL4_CapData	badge	Badge to be applied to the new capability.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.4 CNode - Move

```
static inline int sel4_CNode_Move
```

Move a capability

Type	Name	Description
seL4_CNode	_service	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	dest_index	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	dest_depth	Number of bits of dest_index to resolve to find the destination slot.
seL4_CNode	src_root	CPTR to the CNode that forms the root of the source CSpace. Must be at a depth of 32.
seL4_Word	src_index	CPTR to the source slot. Resolved from the root of the source CSpace.
uint8_t	src_depth	Number of bits of src_index to resolve to find the source slot.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.



### 9.3.5 CNode - Mutate

```
static inline int seL4_CNode_Mutate
```

Move a capability, setting its badge in the process

Type	Name	Description
seL4_CNode	<code>_service</code>	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	<code>dest_index</code>	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	<code>dest_depth</code>	Number of bits of <code>dest_index</code> to resolve to find the destination slot.
seL4_CNode	<code>src_root</code>	CPTR to the CNode that forms the root of the source CSpace. Must be at a depth of 32.
seL4_Word	<code>src_index</code>	CPTR to the source slot. Resolved from the root of the source CSpace.
uint8_t	<code>src_depth</code>	Number of bits of <code>src_index</code> to resolve to find the source slot.
seL4_CapData	<code>badge</code>	Badge to be applied to the new capability.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.6 CNode - Recycle

```
static inline int seL4_CNode_Recycle
```

The recycle method is intended roughly as a short cut for reusing an object within the same protection domain. The method will first revoke the capability and will then reset some but not necessarily all aspects of an object to its neutral state. Recycling badged endpoint caps will only cancel IPCs for this badge. Recycled frames, page tables and directories should only be re-used in the same protection domain, not all authority to them is rescinded. For full reuse in a different protection domain, revoke and retype the untyped cap that was used to create the object. For the precise behaviour of recycle, see the formal specification.

Type	Name	Description
seL4_CNode	_service	CPTR to the CNode at the root of the CSpace where the capability will be found. Must be at a depth of 32.
seL4_Word	index	CPTR to the capability. Resolved from the root of the _service parameter.
uint8_t	depth	Number of bits of index to resolve to find the capability being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.7 CNode - Revoke

```
static inline int seL4_CNode_Revoke
```

Delete all child capabilities of a capability

Type	Name	Description
seL4_CNode	_service	CPTR to the CNode at the root of the CSpace where the capability will be found. Must be at a depth of 32.
seL4_Word	index	CPTR to the capability. Resolved from the root of the _service parameter.
uint8_t	depth	Number of bits of index to resolve to find the capability being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.8 CNode - Rotate

```
static inline int seL4_CNode_Rotate
```

Given 3 capability slots - a destination, pivot and source - move the capability in the pivot slot to the destination slot and the capability in the source slot to the pivot slot

Type	Name	Description
seL4_CNode	<code>_service</code>	CPTR to the CNode at the root of the CSpace where the destination slot will be found. Must be at a depth of 32.
seL4_Word	<code>dest_index</code>	CPTR to the destination slot. Resolved relative to <code>_service</code> . Must be empty unless it refers to the same slot as the source slot.
uint8_t	<code>dest_depth</code>	Depth to resolve <code>dest_index</code> to.
seL4_CapData	<code>dest_badge</code>	The new capdata for the capability that ends up in the destination slot.
seL4_CNode	<code>pivot_root</code>	CPTR to the CNode at the root of the CSpace where the pivot slot will be found. Must be at a depth of 32.
seL4_Word	<code>pivot_index</code>	CPTR to the pivot slot. Resolved relative to <code>pivot_root</code> . The resolved slot must not refer to the source or destination slots.
uint8_t	<code>pivot_depth</code>	Depth to resolve <code>pivot_index</code> to.
seL4_CapData	<code>pivot_badge</code>	The new capdata for the capability that ends up in the pivot slot.
seL4_CNode	<code>src_root</code>	CPTR to the CNode at the root of the CSpace where the source slot will be found. Must be at a depth of 32.
seL4_Word	<code>src_index</code>	CPTR to the source slot. Resolved relative to <code>src_root</code> .
uint8_t	<code>src_depth</code>	Depth to resolve <code>src_index</code> to.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.9 CNode - Save Caller

```
static inline int sel4_CNode_SaveCaller
```

Save the reply capability from the last time the thread was called in the thread's CSpace so that it can be invoked later

Type	Name	Description
sel4_CNode	_service	CPTR to the CNode at the root of the CSpace where the capability will be found. Must be at a depth of 32.
sel4_Word	index	CPTR to the capability. Resolved from the root of the _service parameter.
uint8_t	depth	Number of bits of index to resolve to find the capability being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 3.1.2.

### 9.3.10 Debug - Halt

```
static inline void sel4_DebugHalt
```

Halt the system

Type	Name	Description
void		

*Return value:* This method does not return anything.

*Description:* Halts the system, if debugging is turned on.

### 9.3.11 Debug - Put Character

```
static inline void sel4_DebugPutChar
```

Print a character to the debug console

Type	Name	Description
char	c	The character to print.

*Return value:* This method does not return anything.

*Description:* Prints a character to the serial port, if debugging is turned on.

### 9.3.12 IRQ Control - Get

```
static inline int seL4_IRQControl_Get
```

Create an IRQ handler capability

Type	Name	Description
seL4_IRQControl	_service	An IRQControl capability. This gives you the authority to make this call.
int	irq	The IRQ that you want this capability to handle.
seL4_CNode	root	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	index	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	depth	Number of bits of dest_index to resolve to find the destination slot.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.1

### 9.3.13 IRQ Handler - Acknowledge

```
static inline int seL4_IRQHandler_Ack
```

Acknowledge the receipt of an interrupt and re-enable it

Type	Name	Description
seL4_IRQHandler	_service	The IRQ handler capability.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.1

### 9.3.14 IRQ Handler - Clear

```
static inline int sel4_IRQHandler_Clear
```

Clear the handler capability from the IRQ slot

Type	Name	Description
sel4_IRQHandler	_service	The IRQ handler capability.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.1

### 9.3.15 IRQ Handler - Set Endpoint

```
static inline int sel4_IRQHandler_SetEndpoint
```

Set the endpoint which will receive interrupts controlled by the supplied IRQ handler capability

Type	Name	Description
sel4_IRQHandler	_service	The IRQ handler capability.
sel4_CPtr	endpoint	The endpoint which will receive the IRQs.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.1

### 9.3.16 TCB - Bind Asynchronous Endpoint

```
static inline int sel4_TCB_BindAEP
```

Binds an asynchronous endpoint to a TCB

Type	Name	Description
sel4_TCB	_service	Capability to the TCB which is being operated on.
sel4_CPtr	endpoint	Asynchronous endpoint to bind.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 4.3.2

### 9.3.17 TCB - Unbind Asynchronous Endpoint

```
static inline int seL4_TCB_UnbindAEP
```

Unbinds any asynchronous endpoint from a TCB

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 4.3.2

### 9.3.18 TCB - Configure

```
static inline int seL4_TCB_Configure
```

Set the parameters of a TCB

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.
seL4_Word	fault_ep	CPTR to the endpoint which receives IPCs when this thread faults. This capability is in the CSpace of the thread being configured.
uint8_t	priority	The thread's new priority.
seL4_CNode	cspace_root	The new CSpace root.
seL4_CapData	cspace_root_data	Optionally set the guard and guard size of the new root CNode. If set to zero, this parameter has no effect.
seL4_CNode	vspace_root	The new VSpace root.
seL4_CapData	vspace_root_data	Has no effect on IA-32 or ARM processors.
seL4_Word	buffer	Location of the thread's IPC buffer. Must be 4 byte aligned. The IPC buffer may not cross a page boundary.
seL4_CPtr	bufferFrame	Capability to a page containing the thread's IPC buffer.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1

### 9.3.19 TCB - Copy Registers

```
static inline int sel4_TCB_CopyRegisters
```

Copy the registers from one thread to another

Type	Name	Description
sel4_TCB	_service	Capability to the TCB which is being operated on. This is the destination TCB.
sel4_TCB	source	Cap to the source TCB.
bool	suspend_source	The invocation should also suspend the source thread.
bool	resume_target	The invocation should also resume the destination thread.
bool	transfer_frame	Frame registers should be transferred.
bool	transfer_integer	Integer registers should be transferred.
uint8_t	arch_flags	Architecture dependent flags. These have no meaning on either IA-32 or ARM.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1.2

### 9.3.20 TCB - Read Registers

```
static inline int sel4_TCB_ReadRegisters
```

Read a thread's registers

Type	Name	Description
sel4_TCB	_service	Capability to the TCB which is being operated on.
bool	suspend_source	The invocation should also suspend the source thread.
uint8_t	arch_flags	Architecture dependent flags. These have no meaning on either IA-32 or ARM.
sel4_Word	count	The number of registers to read.
sel4_UserContext*	regs	The structure to read the registers into.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1.5



### 9.3.21 TCB - Resume

```
static inline int seL4_TCB_Resume
```

Resume a thread

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1

### 9.3.22 TCB - Set IPC Buffer

```
static inline int seL4_TCB_SetIPCBuffer
```

Set a thread's IPC buffer

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.
seL4_Word	buffer	Location of the thread's IPC buffer. Must be 4 byte aligned. The IPC buffer may not cross a page boundary.
seL4_CPtr	bufferFrame	Capability to a page containing the thread's IPC buffer.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Sections 5.1 and 4.1

### 9.3.23 TCB - Set Priority

```
static inline int seL4_TCB_SetPriority
```

Change a thread's priority

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.
uint8_t	priority	The thread's new priority.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1.3

### 9.3.24 TCB - Set Space

```
static inline int sel4_TCB_SetSpace
```

Set the fault endpoint, CSpace and VSpace of a thread

Type	Name	Description
sel4_TCB	_service	Capability to the TCB which is being operated on.
sel4_Word	fault_ep	CPTR to the endpoint which receives IPCs when this thread faults. This capability is in the CSpace of the thread being configured.
sel4_CNode	cspace_root	The new CSpace root.
sel4_CapData	cspace_root_data	Optionally set the guard and guard size of the new root CNode. If set to zero, this parameter has no effect.
sel4_CNode	vspace_root	The new VSpace root.
sel4_CapData	vspace_root_data	Has no effect on IA-32 or ARM processors.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1

### 9.3.25 TCB - Suspend

```
static inline int sel4_TCB_Suspend
```

Suspend a thread

Type	Name	Description
sel4_TCB	_service	Capability to the TCB which is being operated on.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1.2

### 9.3.26 TCB - Write Registers

```
static inline int seL4_TCB_WriteRegisters
```

Set a thread's registers

Type	Name	Description
seL4_TCB	_service	Capability to the TCB which is being operated on.
bool	resume_target	The invocation should also resume the destination thread.
uint8_t	arch_flags	Architecture dependent flags. These have no meaning on either IA-32 or ARM.
seL4_Word	count	The number of registers to be set.
seL4_UserContext*	regs	Data structure containing the new register values.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 5.1.5

### 9.3.27 Untyped - Retype

```
static inline seL4_Untyped_Retype_t seL4_Untyped_Retype
```

Retype an untyped object

Type	Name	Description
seL4_Untyped	<code>_service</code>	CPTR to an untyped object.
int	<code>type</code>	The seL4 object type that we are retyping to.
int	<code>size_bits</code>	Only valid for objects with various sizes. Explained below.
seL4_CNode	<code>root</code>	CPTR to the CNode at the root of the destination CSpace.
int	<code>node_index</code>	CPTR to the destination CNode. Resolved relative to the root parameter.
int	<code>node_depth</code>	Number of bits of <code>node_index</code> to translate when addressing the destination CNode.
int	<code>node_offset</code>	Number of slots into the node at which capabilities start being placed.
int	<code>node_window</code>	Maximum number of capabilities to create.

*Return value:* A `seL4_Untyped_Retype_t` structure. The `result` member indicates the number of objects created and the `error` member indicates the returned message tag.

*Description:* Given a capability, `_service`, to an untyped object, create one or more objects of the requested type. Create between 0 and `node_window` capabilities to the new objects starting at `node_offset` in the given CNode. The returned result indicates the number of capabilities created.

The retype method can be complex because multiple capabilities may be created and some objects such as CNodes may have varying sizes.

When an Untyped Memory object is retyped, the number of capabilities (and objects) created depends on the size of the type of object being created, the size of the original piece of untyped memory and the `node_window` parameter passed when invoking the method. The number created is the maximum of the size of the untyped region divided by the size of the type of object being created and the window parameter. If the size of the original Untyped Memory is larger than the required amount of memory then the excess memory is wasted. The required size of each type of object is discussed in Section 9.3.28.

The size of the object(s) being created is determined only by its type for all objects other than CNodes and Untyped Memory. The `size_bits` parameter is used to specify the size of each object to be created in these other two cases. For CNodes, the number of slots in each CNode is calculated as  $2^{\text{size\_bits}}$  and hence the required amount of memory for each is  $16 * 2^{\text{size\_bits}}$ . For the case where Untyped Memory is being split into smaller blocks of Untyped Memory, the size of each of the resulting Untyped Memory blocks is calculated as  $2^{\text{size\_bits}}$ .

The retype method places capabilities to the objects produced at consecutive locations in a CNode. The CNode is specified by the `root`, `node_index` and `node_depth` parameters (see Section 3.3.2). The `node_offset` parameter specifies the index in the CNode at which the first capability will be placed. The `node_window` parameter specifies the

Object	Object Size
$n$ -bit Untyped	$2^n$ bytes (where $n \geq 4$ )
$n$ -slot CNode	$16n$ bytes (where $n \geq 2$ )
Synchronous Endpoint	16 bytes
Asynchronous Endpoint	16 bytes
IRQ Control	—
IRQ Handler	—

**Table 9.1:** Platform Independent Object Sizes

IA-32 Object	Object Size
Thread Control Block	1KiB
IA32 4K Frame	4KiB
IA32 4M Frame	4MiB
IA32 Page Directory	4KiB
IA32 Page Table	4KiB
IA32 ASID Control	—
IA32 ASID Pool	4KiB
IA32 Port	—
IA32 IO Space	—
IA32 IO Page table	4KiB

**Table 9.2:** IA-32 Specific Object Sizes

maximum number of capabilities (and, hence, objects) to create. All slots must be empty or an error will result. All resulting objects will be placed in the same CNode. The retype method must return an error code and the number of objects produced.

### 9.3.28 Summary of Object Sizes

When retyping untyped memory it is useful to know how much memory the object will require. Object sizes are summarised in Tables 9.1, 9.2 and 9.3.

---

ARM Object	Object Size
Thread Control Block	512 bytes
ARM Small Frame	4KiB
ARM Large Frame	64KiB
ARM Section	1MiB
ARM Supersection	16MiB
ARM Page Directory	16KiB
ARM Page Table	1KiB
ARM ASID Control	—
ARM ASID Pool	4KiB

---

**Table 9.3:** ARM Specific Object Sizes

## 9.4 IA-32-Specific Object Methods

### 9.4.1 IA32 ASID Control - Make Pool

```
static inline int seL4_IA32_ASIDControl_MakePool
```

Create an IA-32 ASID pool

Type	Name	Description
seL4_IA32_ASIDControl	_service	The master ASIDControl capability.
seL4_Untyped	untyped	Capability to an untyped memory object that will become the pool. Must be 4K bytes.
seL4_CNode	root	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	index	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	depth	Number of bits of index to resolve to find the destination slot.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.2 IA32 ASID Pool - Assign

```
static inline int seL4_IA32_ASIDPool_Assign
```

Assign an ASID pool

Type	Name	Description
seL4_IA32_ASIDPool	_service	The ASID pool which is being assigned to. Must not be full. Each ASID pool can contain 1024 entries.
seL4_IA32_PageDirectory	vroot	The page directory that is being assigned to an ASID pool. Must not already be assigned to an ASID pool.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.3 IA32 IO Port - In 8

```
static inline seL4_IA32_IOPort_In8_t seL4_IA32_IOPort_In8
```

Read 8 bits from an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to read from.

*Return value:* A seL4\_IA32\_IOPort\_In8\_t structure as described in Section 7.2.1

*Description:* See Section 7.2.1

### 9.4.4 IA32 IO Port - In 16

```
static inline seL4_IA32_IOPort_In16_t seL4_IA32_IOPort_In16
```

Read 16 bits from an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to read from.

*Return value:* A seL4\_IA32\_IOPort\_In16\_t structure as described in Section 7.2.1

*Description:* See Section 7.2.1

### 9.4.5 IA32 IO Port - In 32

```
static inline seL4_IA32_IOPort_In32_t seL4_IA32_IOPort_In32
```

Read 32 bits from an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to read from.

*Return value:* A seL4\_IA32\_IOPort\_In32\_t structure as described in Section 7.2.1

*Description:* See Section 7.2.1



### 9.4.6 IA32 IO Port - Out 8

```
static inline int seL4_IA32_IOPort_Out8
```

Write 8 bits to an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to write to.
uint8_t	data	Data to write to the IO port.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.2.1

### 9.4.7 IA32 IO Port - Out 16

```
static inline int seL4_IA32_IOPort_Out16
```

Write 16 bits to an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to write to.
uint16_t	data	Data to write to the IO port.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.2.1

### 9.4.8 IA32 IO Port - Out 32

```
static inline int seL4_IA32_IOPort_Out32
```

Write 32 bits to an IO port

Type	Name	Description
seL4_IA32_IOPort	_service	An IO port capability.
uint16_t	port	The port to write to.
uint32_t	data	Data to write to the IO port.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.2.1

### 9.4.9 IA32 IO Page Table - Map

```
static inline int sel4_IA32_IOPageTable_Map
```

Map a page table into an IOSpace

Type	Name	Description
sel4_IA32_IOPageTable	_service	The page table that is being mapped.
sel4_IA32_IOSpace	iospace	The IOSpace that the page is being mapped into.
sel4_Word	ioaddr	The address that the page is being mapped at.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.2.2

### 9.4.10 IA32 Page - Map IO

```
static inline int sel4_IA32_Page_MapIO
```

Map a page into an IOSpace

Type	Name	Description
sel4_IA32_Page	_service	The frame that is being mapped.
sel4_IA32_IOSpace	iospace	The IOSpace that the frame is being mapped into.
sel4_CapRights	rights	Rights for the mapping. Possible values for this type are given in Section 3.1.3.
sel4_Word	ioaddr	The address that the frame is being mapped at.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Section 7.2.2

### 9.4.11 IA32 Page - Map

```
static inline int seL4_IA32_Page_Map
```

Map a page into an address space

Type	Name	Description
seL4_IA32_Page	_service	Capability to the page to map.
seL4_IA32_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
seL4_Word	vaddr	Virtual address to map the page into.
seL4_CapRights	rights	Rights for the mapping. Possible values for this type are given in Section 3.1.3.
seL4_IA32.VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.12 IA32 Page - Remap

```
static inline int seL4_IA32_Page_Remap
```

Remap a page

Type	Name	Description
seL4_IA32_Page	_service	Capability to the page to map.
seL4_IA32_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
seL4_CapRights	rights	Rights for the mapping. Possible values for this type are given in Section 3.1.3.
seL4_IA32.VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.13 IA32 Page - Unmap

```
static inline int sel4_IA32_Page_Unmap
```

Unmap a page

Type	Name	Description
sel4_IA32_Page	_service	Capability to the page to unmap.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.14 IA32 Page Table - Map

```
static inline int sel4_IA32_PageTable_Map
```

Map a page table into an address space

Type	Name	Description
sel4_IA32_PageTable	_service	Capability to the page table to map.
sel4_IA32_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
sel4_Word	vaddr	Virtual address to map the page into.
sel4_IA32_VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.4.15 IA32 Page Table - Unmap

```
static inline int sel4_IA32_PageTable_Unmap
```

Unmap a page table from its address space and zero it out

Type	Name	Description
sel4_IA32_PageTable	_service	Capability to the page table to unmap.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

## 9.5 ARM-Specific Object Methods

### 9.5.1 ARM ASID Control - Make Pool

```
static inline int seL4_ARM_ASIDControl_MakePool
```

Create an ASID Pool

Type	Name	Description
seL4_ARM_ASIDControl	_service	The master ASIDControl capability.
seL4_Untyped	untyped	Capability to an untyped memory object that will become the pool. Must be 4K bytes.
seL4_CNode	root	CPTR to the CNode that forms the root of the destination CSpace. Must be at a depth of 32.
seL4_Word	index	CPTR to the destination slot. Resolved from the root of the destination CSpace.
uint8_t	depth	Number of bits of index to resolve to find the destination slot.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.2 ARM ASID Pool - Assign

```
static inline int seL4_ARM_ASIDPool_Assign
```

Assign an ASID Pool

Type	Name	Description
seL4_ARM_ASIDPool	_service	The ASID pool which is being assigned to. Must not be full. Each ASID pool can contain 1024 entries.
seL4_ARM_PageDirectory	vroot	The page directory that is being assigned to an ASID pool. Must not already be assigned to an ASID pool.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.3 ARM Page - Flush Caches

```
static inline int seL4_ARM_Page_FlushCaches
```

Flush a cache range

Type	Name	Description
seL4_ARM_Page	_service	The page whose contents will be flushed.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.4 ARM Page - Map

```
static inline int seL4_ARM_Page_Map
```

Map a page into an address space

Type	Name	Description
seL4_ARM_Page	_service	Capability to the page to map.
seL4_ARM_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
seL4_Word	vaddr	Virtual address to map the page into.
seL4_CapRights	rights	Rights for the mapping. Possible values for this type are given in Section 3.1.3.
seL4_ARM_VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.5 ARM Page - Remap

```
static inline int seL4_ARM_Page_Remap
```

Remap a page

Type	Name	Description
seL4_ARM_Page	_service	Capability to the page to remap.
seL4_ARM_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
seL4_CapRights	rights	Rights for the mapping. Possible values for this type are given in Section 3.1.3.
seL4_ARM_VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.6 ARM Page - Unmap

```
static inline int seL4_ARM_Page_Unmap
```

Unmap a page

Type	Name	Description
seL4_ARM_Page	_service	Capability to the page to unmap.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.7 ARM Page Table - Map

```
static inline int seL4_ARM_PageTable_Map
```

Map a page table into an address space

Type	Name	Description
seL4_ARM_PageTable	_service	Capability to the page table that will be mapped.
seL4_ARM_PageDirectory	pd	Capability to the VSpace which will contain the mapping.
seL4_Word	vaddr	Virtual address to map the page into.
seL4_ARM_VMAttributes	attr	VM Attributes for the mapping. Possible values for this type are given in Chapter 6.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6

### 9.5.8 ARM Page Table - Unmap

```
static inline int seL4_ARM_PageTable_Unmap
```

Unmap a page table from its address space and zero it out

Type	Name	Description
seL4_ARM_PageTable	_service	Capability to the page table that will be unmapped.

*Return value:* The returned message tag. 0 indicates success. A non-zero value indicates that an error occurred. See Section 9.1 for a description of the message register and tag contents upon error.

*Description:* See Chapter 6



# Bibliography

- [BBD<sup>+</sup>09] Andrew Baumann, Paul Barham, Pierre-Evariste Dagand, Tim Harris, Rebecca Isaacs, Simon Peter, Timothy Roscoe, Adrian Schüpbach, and Akhilesh Singhania. The multikernel: A new OS architecture for scalable multicore systems. In *22nd Symposium on Operating System Principles*, Big Sky, MT, USA, Oct 2009. ACM.
- [Boy09] Andrew Boyton. A verified shared capability model. In Gerwin Klein, Ralf Huuck, and Bastian Schlich, editors, *4th Systems Software Verification*, volume 254 of *Electronic Notes in Theoretical Computer Science*, pages 25–44, Aachen, Germany, Oct 2009. Elsevier.
- [CKS08] David Cock, Gerwin Klein, and Thomas Sewell. Secure microkernels, state monads and scalable refinement. In Otmane Ait Mohamed, César Muñoz, and Sofiène Tahar, editors, *21st Theorem Proving in Higher Order Logics*, volume 5170 of *LNCS*, pages 167–182, Montreal, Canada, Aug 2008. Springer-Verlag.
- [DEK<sup>+</sup>06] Philip Derrin, Kevin Elphinstone, Gerwin Klein, David Cock, and Manuel M. T. Chakravarty. Running the manual: An approach to high-assurance microkernel development. In *ACM SIGPLAN Haskell Workshop*, Portland, OR, USA, Sep 2006.
- [EKE08] Dhammika Elkaduwe, Gerwin Klein, and Kevin Elphinstone. Verified protection model of the seL4 microkernel. In Jim Woodcock and Natarajan Shankar, editors, *Verified Software: Theories, Tools and Experiments 2008*, volume 5295 of *LNCS*, pages 99–114, Toronto, Canada, Oct 2008. Springer-Verlag.
- [Int08] *Intel Virtualisation Technology for Directed I/O Architecture Specification*, September 2008.
- [KEH<sup>+</sup>09] Gerwin Klein, Kevin Elphinstone, Gernot Heiser, June Andronick, David Cock, Philip Derrin, Dhammika Elkaduwe, Kai Engelhardt, Rafal Kolanski, Michael Norrish, Thomas Sewell, Harvey Tuch, and Simon Winwood. seL4: Formal verification of an OS kernel. In *22nd Symposium on Operating System Principles*, pages 207–220, Big Sky, MT, USA, Oct 2009. ACM.
- [Pal08] Ameya Palande. Capability-based secure DMA in seL4. Master’s thesis, Vrije Universiteit, Amsterdam, November 2008.

- [SA99] Tom Shanley and Don Anderson. *PCI System Architecture*. Mindshare, Inc., 1999.
- [TKN07] Harvey Tuch, Gerwin Klein, and Michael Norrish. Types, bytes, and separation logic. In Martin Hofmann and Matthias Felleisen, editors, *34th Principles of Programming Languages*, pages 97–108, Nice, France, Jan 2007.
- [vT10] Michael von Tessin. Towards high-assurance multiprocessor virtualisation. In *6th Verify*, Edinburgh, UK, Jul 2010.
- [WKS<sup>+</sup>09] Simon Winwood, Gerwin Klein, Thomas Sewell, June Andronick, David Cock, and Michael Norrish. Mind the gap: A verification framework for low-level C. In Stefan Berghofer, Tobias Nipkow, Christian Urban, and Makarius Wenzel, editors, *22nd Theorem Proving in Higher Order Logics*, volume 5674 of *LNCS*, pages 500–515, Munich, Germany, Aug 2009. Springer-Verlag.